Journal of Solar Energy Engineering

Copy of e-mail Notification

Journal of Solar Energy Engineering Published by ASME

Dear Author,

Congratulations on having your paper accepted for publication in the ASME Journal Program.

Your page proof is available from the ASME Proof site here:

<http://cps.kwglobel.com/MIS/AuthorProofLogin.aspx?pwd=9887d1dbb8cb&CA=AS>

Login: your e-mail address

Password: 9887d1dbb8cb

Please keep this email in case you need to refer back to it in the future.

Responsibility of detecting errors rests with the author. Please review the page proofs carefully and:

1. Answer any queries on the "Author Query Form"
2. Proofread any tables and equations carefully
3. Check to see that any special characters have translated correctly
4. Publication will not proceed until a response is received. If there are no corrections, a response is still required.

RETURNING CORRECTIONS:

Corrections must be returned using the ASME Proof Download & Corrections Submission Site (link above). You will be able to upload:

1. Annotated PDF
2. Text entry of corrections, with line numbers, in the text box provided
3. Additional files, if necessary.

SPECIAL NOTES:

Your Login and Password are valid for a limited time. Please reply within 48 hours.

Corrections not returned through the above website will be subject to publication delays.

This e-proof is to be used only for the purpose of returning corrections to the publisher. Please note, the figures in this proof are low resolution, the final paper will publish with all figures as 300 dpi. If you have any questions, please contact: asme.cenveo@cenveo.com, and include your article no. (SOL-18-1406) in the subject line. This email should not be used to return corrections.

Approval of these proofs re-confirms the copyright agreement provision that all necessary rights from third parties for any copyrighted material (including without limitation any diagrams, photographs, figures or text) contained in the paper has been obtained in writing and that appropriate credit has been included.

Sincerely,

Mary O'Brien, Journal Production Manager

STATEMENT OF EDITORIAL POLICY AND PRACTICE

The Technical Committee on Publications and Communications (TCPC) of ASME aims to maintain a high degree of technical, literary, and typographical excellence in its publications. Primary consideration in conducting the publications is therefore given to the interests of the reader and to safeguarding the prestige of the Society.

To this end the TCPC confidently expects that sponsor groups will subject every paper recommended by them for publication to careful and critical review for the purpose of eliminating and correcting errors and suggesting ways in which the paper may be improved as to clarity and conciseness of expression, accuracy of statement, and omission of unnecessary and irrelevant material. The primary responsibility for the technical quality of the papers rests with the sponsor groups.

In approving a paper for publication, however, the TCPC reserves the right to submit it for further review to competent critics of its own choosing if it feels that this additional precaution is desirable. The TCPC also reserves the right to request revision or condensation of a paper by the author or by the staff for approval by the author. It reserves the right, and charges the editorial staff, to eliminate or modify statements in the paper that appear to be not in good taste and hence likely to offend readers (such as obvious advertising of commercial ventures and products, comments on the intentions, character, or acts of persons and organizations that may be construed as offensive or libelous), and to suggest to authors rephrasing of sentences where this will be in the interest of clarity. Such rephrasing is kept to a minimum.

Inasmuch as specific criteria for the judging of individual cases cannot, in the opinion of the TCPC, be set up in any but the most general rules, the TCPC relies upon the editorial staff to exercise its judgment in making changes in manuscripts, in rearranging and condensing papers, and in making suggestions to authors. The TCPC realizes that the opinions of author and editor may sometimes differ, and hence it is an invariable practice that no paper is published until it has been passed on by the author. For this purpose page proofs of the edited paper are sent to the author prior to publication in a journal. Changes in content and form made in the proofs by authors are followed by the editor except in cases in which the Society's standard spelling and abbreviation forms are affected.

If important differences of opinion arise between author and editor, the points at issue are discussed in correspondence or interview, and if a solution satisfactory to both author and editor is not reached, the matter is laid before the TCPC for adjustment.

Technical Committee on Publications and Communications (TCPC)
Reviewed: 05/2012

AUTHOR QUERY FORM

<p>Journal: J. Sol. Energy Eng.</p> <p>Article Number: SOL-18-1406</p>	<p>Please provide your responses and any corrections by annotating this PDF and uploading it to ASME's eProof website as detailed in the Welcome email.</p>
---	---	--

Dear Author,

Below are the queries associated with your article; please answer all of these queries before sending the proof back to Cenveo. Production and publication of your paper will continue after you return corrections or respond that there are no additional corrections.

Location in article	Query / Remark: click on the Q link to navigate to the appropriate spot in the proof. There, insert your comments as a PDF annotation.
AQ1	Reminder – the ASME Copyright Agreement that was signed by all authors includes the following: “You have the right to enter into this Copyright Form and to make the assignment of rights to ASME. If the Paper contains excerpts from other copyrighted material (including without limitation any diagrams, photographs, figures or text), you have acquired in writing all necessary rights from third parties to include those materials in the Paper, and have provided appropriate credit for that third-party material in footnotes or in a bibliography.” As required, ASME may contact the authors to obtain a copy of the written permission.
AQ2	Any content obtained from the web and included in the paper may require written permission and appropriate credit if it is copyrighted content. If copyright status cannot be determined, this content should not be included in the paper.
AQ3	Please note the figures in this proof are low resolution, the final paper will publish with all figures as 300 dpi.
AQ4	Please check the presentation of all the affiliations.
AQ5	Please provide department details, city, state, zip code for present address.
AQ6	References 18 and 23 were not cited in text. Please check its insertion.
AQ7	Please define PV at first occurrence.
AQ8	References must be cited in numerical order. Please check renumbering of Refs. 24–28.
AQ9	Please note that bold roman is generally used to designate vectors/matrices/tensors. Therefore, is lightface italic OK for vector/matrix/tensor designation or would you prefer bold roman for vector/matrix/tensor notation? If vectors/matrices/tensor should be bold roman, please highlight the variables that need to be bold.
AQ10	Please provide location (city and state/country) for the manufacturers.
AQ11	As per style, “et al.” is not allowed in the reference list. Please provide the full list of authors for Refs. 4, 9, 13, and 32.
AQ12	Please provide conference held location and date for Refs. 10 and 13.
AQ13	Please provide conference held location and date and page range/paper number for Ref. 15.
AQ14	Please provide page number in range for Refs. 19 and 31.
AQ15	Please provide publisher name and location (city and state/country) for Refs. 20, 25, and 34.
AQ16	Please provide complete bibliographic details for Refs. 26, 27, and 33.
AQ17	Please note that there were two sets of figure captions given in the PDF, one at the end of the article and other below the respective diagrams, we have set the captions matching with the ones given below the respective diagrams. Please check.
AQ18	Please provide DOI or website to access article for Ref(s). 1.

Thank you for your assistance.

AQ1
AQ2
AQ3

AQ4

Mostafa Abuseada

High Flux Gas Dynamics Laboratory,
Mechanical and Industrial
Engineering Department,
University of Minnesota Duluth,
Duluth, MN 55812

Cedric Ophoff¹

Solar Thermal Technology Laboratory,
Mechanical Engineering Department,
KU Leuven,
Leuven 3001, Belgium

Nesrin Ozalp²

Fellow ASME
High Flux Gas Dynamics Laboratory,
Mechanical and Industrial Engineering
Department,
University of Minnesota Duluth,
Duluth, MN 55812
e-mail: nozalp@d.umn.edu

Characterization of a New 10 kW_e High Flux Solar Simulator Via Indirect Radiation Mapping Technique

This paper presents characterization of a new high flux solar simulator consisting of a 10 kW Xenon arc via indirect heat flux mapping technique for solar thermochemical applications. The method incorporates the use of a heat flux gauge (HFG), single Lambertian target, complementary metal oxide semiconductor (CMOS) camera, and three-axis optical alignment assembly. The grayscale values are correlated to heat flux values for faster optimization and characterization of the radiation source. Unlike previous work in heat flux characterization that rely on two Lambertian targets, this study implements the use of a single target to eliminate possible errors due to interchanging the targets. The current supplied to the simulator was varied within the range of 120–200 A to change the total power and to mimic the fluctuation in sun's irradiance. Several characteristic parameters of the simulator were studied, including the temporal instability and radial nonuniformity (RNU). In addition, a sensitivity analysis was performed on the number of images captured, which showed a threshold value of at least 30 images for essentially accurate results. The results showed that the flux distribution obtained on a $10 \times 10 \text{ cm}^2$ target had a peak flux of 6990 kWm^{-2} , total power of 3.49 kW, and half width of 6.25 mm. The study concludes with the illustration and use of a new technique, the merging method, that allows characterization of heat flux distributions on larger areas, which is a promising addition to the present heat flux characterization techniques.

[DOI: 10.1115/1.4042246]

Author Proof

22 Introduction

Experimental testing of solar receivers/reactors for thermal and thermochemical applications requires controllable source of high flux radiation mimicking the intensity of solar spectrum at different wavelengths. High flux radiation simulators comprise one or more lamps each equipped with an ellipsoidal reflector focusing the rays to a common focal point where the flux of radiation is concentrated [1]. Xenon arc, metal halide, and Argon lamps are the most commonly used types in high flux simulators [2,3]. Xenon and metal halide lamps exhibit radiation peaks in the wavelength range of 800–1000 nm while Argon lamps exhibit peaks in the 700–1000 nm range which are the most notable deviations from the sun's direct normal irradiance spectrum [1].

High flux solar simulators (HFSS) are characterized based on the type of lamp and the electrical power input versus the peak flux delivered. The literature shows that the highest power consuming solar simulator is a single Argon lamp of $\sim 200 \text{ kW}_e$, which is capable of delivering lower to moderate power densities of around 5000 kWm^{-2} [2]. On the other hand, metal halide lamps deliver the lowest power densities with less than 2000 kWm^{-2} at power consumption of less than 50 kW_e . As for the Xenon lamps, there is a broad range of power requirements and densities with the possibility of reaching the highest peak fluxes of more than $15,000 \text{ kWm}^{-2}$ [2]. An overview of several different HFSS types is shown in Table 1.

Although most HFSSs use several lamps to achieve radiation concentrations and temperatures that are of most interest to researchers, there has been some work on smaller scale reactors using single-lamp setups that are up to 10 kW_e input power. For example, a single-lamp setup can be created from an off-the-shelf cinema projector as described in Refs. [10] and [14], where a 7 kW_e Xenon arc lamp was tested similar to the experiments done in Ref. [15]. Single-lamp simulators can be used with solar reactors to characterize the kinetics of metal oxides reduction [16] and thermochemical water-splitting using ferrite [17], in addition to other applications [18]. There are also single-lamp simulators with considerably higher power input. For example, a single Xenon lamp at Berkeley laboratory was $20\text{--}30 \text{ kW}_e$ [11].

There are many multilamp simulator designs operating in $40\text{--}50 \text{ kW}_e$ range, which is an optimal size for laboratory-scale reactors [8,15–17]. For example, an array of seven Xenon arc lamps is used in both Refs. [12] and [19], and very similar HFSSs rated $\sim 40 \text{ kW}_e$ were also developed at Georgia Institute of Technology (GIT) [7], University of Florida [20], Swinburne University [3], and Instituto Madrileño De Estudios Avanzados (IMDEA) [12], whereas 18 lamps are used in Ref. [8] and ten 15 kW_e are used at the Swiss Federal Institute of Technology Zurich (Eidgenössische Technische Hochschule Zürich—ETH) [4]. The German Aerospace Center (DLR) recently created “the world's largest artificial sun” called Synlight which consists of 149 Xenon arc lamps [13]. The system is capable of producing 280 kW or two 220 kW for processes using two simultaneously heated chambers in three separate radiation chambers.

In some solar thermal applications, it may be of interest to create a uniform flux as opposed to a highly focused flux. For example, flat plate solar collectors such as panels should be tested under uniform flux resembling the natural solar irradiance, because a concentrating unit is not necessarily used for flat plate

AQ5

¹Present address: University of Minnesota Duluth, .²Corresponding author.

Contributed by the Solar Energy Division of ASME for publication in the JOURNAL OF SOLAR ENERGY ENGINEERING: INCLUDING WIND ENERGY AND BUILDING ENERGY CONSERVATION. Manuscript received September 3, 2018; final manuscript received November 8, 2018; published online xx xx, xxxx. Guest Editors: Tatsuya Kodama, Christian Sattler, Nathan Siegel, Ellen Stechel.

Table 1 Comparison of high flux solar simulators, their performance metrics, and flux characterization method

Institute	Lamp type	No. of lamps	Peak flux (kW m ⁻²)	Electric/radiative power (kW _e /kW)	Flux characterization method
ETH—[4]	15 kW _e Xenon	10	11,000	150/50	Calibrated CCD + Kendall radiometer
Bucknell University—[5]	2.5 kW _e Metal Halide	4	1140	10/3.5	Calibrated camera + calorimeter
KTH—[6]	7 kW _e Xenon	12	6360	84/20.3	Thermopile flux sensor
GIT—[7]	6 kW _e Xenon	7	6834	42/6.1	Calibrated CCD + calorimeter
ANU/EPFL—[8]	2.5 kW _e Xenon	18	21,700	45/7.5	Calibrated CCD + Vatel TG1000-0 flux transducer
CIO—[9]	2.5 kW _e Xenon	7	194 per lamp	17.5/—	Gardon–Schmidt–Boelter heat flux sensor + CCD
KU Leuven—[10]	7 kW _e Xenon	1	3158	7/0.9	Calibrated CMOS + Vatel TG1000-0 flux transducer
Berkeley—[11]	20 kW _e Xenon	1	16,000	20/3	Model 1000-0 Thermogage
IMDEA—[12]	6 kW _e Xenon	7	3600	42/14	Calibrated CCD + Vatel TG1000-0 flux transducer
DLR—[13]	7 kW _e Xenon	149	>11,000	1043/280 or 2 × 220	—

collectors. As an example, a recent design used a virtual imaging approach to create a very uniform radiation flux [21], where four halogen lamps were used along with an internally reflective container to translate the point source of light from the lamps into a uniform flux, which was evaluated by a two-dimensional array of thermocouples placed on the surface of the prototype solar collector. However, it should be noted that there are several differences between solar simulators used for solar thermal applications and solar simulators used for photovoltaic research. Solar simulators used in photovoltaic research do not mimic the sun’s concentrated radiation spectrum. Furthermore, because the performance of a PV panel is affected by the sun’s angle relative to the normal angle of the panel and the change in air mass between the solar source and the panel throughout the day, PV solar simulators must be able to simulate these effects [22]. These help to accurately characterize the expected performance of different cells for different parts of the world and for different types of installation, such as tracking, nontracking, and rooftop installations [23]. The American Society of Testing and Materials (ASTM) as well as the International Electrotechnical Commission (IEC) classify solar simulators according to three criteria: spectral match, spatial non-uniformity of irradiance, and temporal stability [22].

In this work, heat flux characterization of a new 10 kW_e single-source HFSS is performed using the indirect radiation mapping method. The power of the source is varied by changing the current supplied to the simulator to determine the heat flux map at several power levels. A sensitivity analysis is performed to inspect the impact of number of captured images on the accuracy and consistency of the experimental results. In addition to the quantification of the HFSS’s transient response upon startup, temporal instability, and radial nonuniformity, a new method is proposed to identify flux distributions on larger areas within the focal plane.

Methodology

The first step in characterizing a solar simulator is to have a method that can accurately measure the radiant heat flux output. A heat flux gauge (HFG) can be used to measure the flux distribution directly using a direct mapping technique or will allow the correlation of grayscale values from a camera to characterize the simulator using an indirect mapping method. HFGs provide a voltage output in the scale of millivolts, which needs to be calibrated to obtain flux density values in kWm⁻². Calibration of a HFG can be either performed in-house as explained in Refs. [24] and [25], or the calibration provided by the manufacturer can be used. An important consideration that should be taken into account is the relative size of the HFG sensor to the spot size of the measured flux density distribution. In this study, the active gage area has a diameter of 1.016 mm which is an order of magnitude smaller than the observed spot size and can, therefore, be considered suitable for this measurement campaign.

For an indirect mapping method, the heat flux density values obtained using HFG should be correlated to grayscale values obtained from charged coupled device (CCD) camera or

complementary metal oxide semiconductor (CMOS) camera. A diffusively reflecting (Lambertian) target is placed at the plane of interest to capture the flux density distribution using the grayscale values of the camera. An accurate positioning of the target is required to get the most precise focal point and flux density distribution. When the camera is placed coaxially with the target as in Ref. [8], the images can be captured and processed with no additional postprocessing. However, most experimental setups do not allow coaxial image capturing due to direct exposure to the light beam. Hence, the camera is placed with an angle to the target, i.e., *observer’s angle*, which requires postprocessing via a geometric transformation to get the undistorted image of the target as shown in Fig. 1. This is performed through rectifying and scaling the image using a projective transformation method, where images in raw format are recommended and the image should not be saturated. Through this spatial transformation method, straight lines and quadrilaterals keep their geometries. The method of transforming from point $P'(x', y')$ to point $P(x, y)$ is illustrated through the following equations, and visualized in Fig. 1, where the transformation matrix T is defined as

Fig. 1 Rectification of the transformed image

$$x = \frac{c_{11}x' + c_{21}y' + c_{31}}{c_{13}x' + c_{23}y' + c_{33}} \quad (1)$$

$$y = \frac{c_{12}x' + c_{22}y' + c_{32}}{c_{13}x' + c_{23}y' + c_{33}} \quad (2)$$

$$T = \begin{bmatrix} c_{11} & c_{12} & c_{13} \\ c_{21} & c_{22} & c_{23} \\ c_{31} & c_{32} & c_{33} \end{bmatrix} \quad (3)$$

The transformation matrix shown in Eq. (3) has nine coefficients that need to be solved to successfully complete the projective transformation. Although T has nine coefficients, it only has eight degrees-of-freedom, since c_{33} is an arbitrary scale coefficient and it can be set to one. Hence, there are only eight coefficients to solve using four sets of points. The coefficients in T depends on the exact position of the camera, and therefore, it can significantly differ from one experimental setup to the other. Transformation matrix given in the following equation is being used throughout the characterization of the HFSS in this study:

$$T = \begin{bmatrix} 0.4991 & -0.0138 & -6.8904 \times 10^{-5} \\ -0.0265 & 0.7841 & -3.0045 \times 10^{-6} \\ 459 & 144 & 1 \end{bmatrix} \quad (4)$$

To determine the optimum number of images to be captured by the camera, a statistical measure based on the root-mean-square error (RMSE) is implemented. The parameters tested are the total power on a $10 \times 10 \text{ cm}^2$ target and maximum deviation at any point from the allegedly real value based on a total of 300 captured images.

Concentrated solar radiation especially from a single reflector is very uniform and symmetric in its distribution. To be able to mimic the behavior of concentrated solar radiation, it is crucial to define an index that expresses the level of symmetry in the distribution obtained from the solar simulator. Therefore, a radial non-uniformity (RNU) index has been implemented here, which is very similar to the spatial uniformity index, but is taken across annular areas centered at the focal point. This expresses the percentage deviation of the obtained flux density from a symmetrical circular distribution. The RNU is defined as shown in the

following equation, where $q''_{\max}$ and $q''_{\min}$ are the maximum and minimum values of heat flux density at a given time and radius from the target's center:

$$\text{RNU}(\%) = \frac{q''_{\max} - q''_{\min}}{q''_{\max} + q''_{\min}} \times 100 \quad (5)$$

The temporal instability is a characteristic for classification of solar simulators, and it quantifies the relative change of irradiance over time for a specified time period. According to ASTM E927 and IEC 60904-9, solar simulators can be classified into three classes based on their temporal instability values; class A for values up to 2%, class B for 5%, and class C for 10% [24,25]. The temporal instability is calculated analogously to the RNU as shown in the following equation, where $q''_{\max}$ and $q''_{\min}$ are the maximum and minimum values of heat flux density at a given position throughout a time period

$$\text{TI}(\%) = \frac{q''_{\max} - q''_{\min}}{q''_{\max} + q''_{\min}} \times 100 \quad (6)$$

While most of the previous flux characterization studies implemented the use of two Lambertian targets, where the HFG would be embedded in one while the second target would serve for image capturing [14,26], this study demonstrates characterization of the solar simulator using one target. This eliminates misalignment errors that would otherwise occur when interchanging targets. The single target used in this work covers a square area of $35 \times 35 \text{ cm}^2$ and comprises a hole at the center to house the heat flux gauge as illustrated in Fig. 1. As a result, the continuous reflective area on the target only allows to map the heat flux density on a maximum target size of $16.6 \times 16.6 \text{ cm}^2$.

Extension of this work led to a new method to increase the focal area size on which the flux density can be measured, referred to as the *merging method*. The target was displaced 3 cm from its center in both vertical and horizontal directions within the focal plane as illustrated in Fig. 2. This yields flux maps for five different target positions: *center*, *upper right*, *upper left*, *lower left*, and *lower right*. The flux data obtained were merged through postprocessing into one larger data matrix. Flux density values of overlapping areas were averaged, while values inside the heat gauge area shown as dashed circles in Fig. 2 were omitted using logical

Fig. 2 Configuration of the Lambertian target for the merging method

Fig. 3 (a) Schematic illustration of the overall experimental setup and (b) photo of experimental setup

operations. The maximum dimensions of the final flux map are determined by the displacements of the target. In this study, the dimensions were set to 35 × 35 cm².

Experimental Setup and Procedure

The experimental setup consists of a lamp house with an installed 10 kW_e Xenon arc, a heat flux gauge, 35 × 35 cm² Lambertian target, CMOS camera with optical filters, XYZ slider assembly with a motion controller, and a data acquisition system. The setup is depicted in Fig. 3(a), whereas a photo of the experimental setup is shown in Fig. 3(b).

The solar simulator is manufactured by Strong Lighting (Fig. 4), and it consists of an ellipsoidal reflector with truncated diameters of 9 cm and 39 cm in addition to two focal points at 7.5 cm and 82.5 cm from the vertex. The simulator comes

equipped with intake blowers and an exhaust fan to ventilate the lamp house’s interior and prevent the bulb from overheating. A power switch is used to control the power supplied to the lamp by controlling the current supplied within the range of 80–200 A. Since the nominal current for the 10 kW Xenon bulb is 200 A, the preferred range of controlling the bulb is within 160–200 A or as low as 80% of the nominal current to avoid instabilities within the arc and to preserve the condition of the bulb [27]. However, the supply current can be adjusted as low as 50% given that it does not continuously run on at low current values. Therefore, the current supplied to the Xenon bulb for testing is varied from 120 to 200 A with the increments of 5 A.

The HFG used in experiments is provided by Vatec model number TG1000-0, which can measure flux densities that are up to approximately 7500 kWm^{−2} without damaging the sensor or losing its calibration. The gage has a sensor coated with colloidal

Fig. 4 Overview of the high flux solar simulator and its components

Fig. 5 Configuration of the Lambertian target, with K-type thermocouples to monitor its cooling

graphite that has an emissivity of 0.82. The output voltage of the HFG lies within the range of 0–15 mV with an accuracy of $\pm 3\%$. The gauge was calibrated by the company, where it had a linear relationship with a sensor scale factor for absorbed radiant heat flux of $492.59 \text{ kWm}^{-2}/\text{mV}$, for the aforementioned voltage output range. Exceeding this range will produce a nonlinear output, and hence, the calibration will no longer be valid. It should be noted that the calibration done by the manufacturer may lead to overestimating the flux density values by up to 30% of the real values as discussed by Krueger due to a mismatch between the radiation spectrum used for calibration and that used in solar applications [26]. Krueger recommended the use of a third-order polynomial relating the output voltage to heat flux density, whereas other researchers have used linear relationships through in-house calibrations, or verified the use of the calibration provided by Vatel [8,28–30]. A comparison of the calibration provided by Vatel and of that performed in-house by CIEMAT shows that both values agree with an error of 3.6%, which lies within the uncertainties of both calibration coefficients making the sensor scale factor provided by Vatel accurate enough to claim reliable [28].

A $35 \times 35 \text{ cm}^2$ water-cooled Lambertian target provided by Haueter Engineering Company was used to diffusely reflect the incident flux from the simulator at any plane of interest. The target has an aluminum body coated with alumina at the front side, a 25.4 mm opening in the center to house the heat gauge, two water inlets at the top, and two water outlets at the bottom as shown in Fig. 5. In order to control the position of the target accurately to determine the focal point and to precisely measure the flux density distribution, the assembly was mounted onto an XYZ slider configuration provided by Newmark Corporation. The XYZ slider is driven through a motion controller with a very high resolution of $0.08 \mu\text{m}$ that is capable of up to a maximum linear travel of 0.2 m, 0.3 m, and 0.5 m for the x -, y -, and z -axis, respectively. With such high resolution, the movement of the target assembly is very accurate, and it enables high repeatability of measurements granting precise testing of some parameters such as the inverse ray tracing of the radiative flux from the bulb. To ensure consistency of measurements, the temperature of the inlet water, outlet water, and across the target's body was monitored using type-K thermocouple probes for the inlet and outlets in addition to four bolt-on

thermocouples mounted at the back of the target via an arrangement shown in Fig. 5.

Once the Lambertian target is placed at the theoretical focal point, i.e., 82.5 cm from the reflector vertex, the next step is to calibrate the CMOS camera. The camera used in this study is model BlueCOUGAR X104fg provided by Matrikon which has resolution of 1936×1216 pixels and a pixel size of $5.86 \mu\text{m} \times 5.86 \mu\text{m}$. The camera is equipped with a lens that has two neutral density filters of absorptive 1% transmission and absorptive 0.01% transmission in order to protect the camera's sensors from damage due to exposure to high flux and also ensure that the image is not saturated. Use of neutral density filters significantly reduces the possibility of white "hot pixels" formation due to damages resulting in an increased leakage of current, which could cause major distortions to the captured grayscale images [31]. Once the camera is set, the HFG is used to measure the heat flux at the focal point and at uniaxial distances across the focal plane along the positive and negative horizontal and vertical directions. The CMOS camera is then used to capture the raw grayscale images of the heat flux density distribution on the target, where the gain and exposure time of the camera needs to be adjusted. This in turn affects the amplification of the analog-to-digital conversion of signals to ensure that the peak grayscale value is approximately 75% of the full-scale value of 255. This is done to achieve maximum accuracy for the measurements while avoiding the saturation of captured images. Once images are captured, they are processed to obtain grayscale values with respect to the position across the focal plane. Grayscale values can then be correlated to heat flux density values, using a linear fit based on the least squares method. A linear fit is chosen for the correlation of the grayscale values based on the experimental results obtained, linear response of the CMOS camera with respect to light intensity, surface properties of the Lambertian target, and finally the previous work of other researchers in the field [8,12,14], where it is clear that there is a linear relationship between the grayscale and heat flux density values.

A data acquisition system using LabVIEW and hardware from National Instruments (NI) was implemented to have real-time data monitor and collection. The system consisted of cRIO 9030 to connect up to four modules in addition to NI-9214 temperature input module which can connect up to 16 sensors and has a minimum voltage increment of $9.3 \mu\text{V}$. The temperature input module has resolution of 24 bits, and voltage measurement range of $\pm 78.125 \text{ mV}$. This makes it much superior for heat flux measurements than the analog input module NI-9215 which has resolution of 16 bits and voltage measurement range of $\pm 10 \text{ V}$. Initially, the data acquisition system was used to achieve two main purposes; to monitor temperatures within the Lambertian target to ensure uniform cooling, and to measure heat flux density values using the HFG. For all experimental runs, the solar simulator was operated for 15–30 min at start-up before acquiring measurements due to the transient nature of the Xenon arc and solar simulators. As shown in Ref. [26], and shown later in the Results section of this study, solar simulators exhibit a well-defined "long-term temporal behavior," where the heat flux density distribution from the lamp increases upon ignition as time progresses. In Ref. [26], the initial irradiance obtained right after ignition was around 750 kWm^{-2} , which increased to around 925 kWm^{-2} within an hour approximately, exhibiting a nonlinear behavior that levels off in about 15 min. Moreover, the transient behavior of the lamp in Ref. [8] was also determined to reach a steady-state, where intensity variations were less than 5%, after 10 min of data collection.

The bulb was optically aligned in order to identify the highest peak flux density, power, and uniformity by adjusting its position in three axes. Using the correlation between grayscale and irradiance values already established, it was straightforward to observe and quantify the effect of any changes made during alignment. This is an advantage of indirect heat flux mapping method over direct heat flux mapping methods where it would take much longer to completely quantify the effects and properly align the bulb.

Fig. 6 Correlation of measured heat flux density and corresponding grayscale values, with error bars presenting uncertainty of each measurement

Results and Discussion

Calibration of Grayscale Values. The HFG was used to measure the heat flux density distribution at the focal plane starting from the origin at zero and reaching to a maximum radius of 65 mm. This was performed for the positive and negative horizontal and vertical axes along the focal plane, where the HFG was moved in a uniaxial manner to get the distribution along both axes. Starting from the origin, the HFG was moved up to 15 mm with increments of 0.5 mm, then from 15 to 30 mm with increments of 1 mm, and finally from 30 to 65 mm with increments of 5 mm. This ensured that the heat flux data collected covers the entire range of the distribution emitted by the bulb. The CMOS camera was then used to capture raw grayscale images that were then processed and correlated to heat flux values at the same location.

The correlation of the measured heat flux density values and corresponding grayscale values is shown in Fig. 6. The calibration equation was determined to be $y = 31.562x \pm 66 \text{ kWm}^{-2}$, not taking into account the calibration standard's uncertainty (HFG) of

3% and at a 95% confidence interval, where y is the flux density in kWm^{-2} , and x is the grayscale value. This correlation was obtained after optimizing the alignment of the bulb toward higher peak flux densities. Correlations prior to the alignment of the bulb would result in the CMOS camera reaching its saturation point, i.e., the increasing heat flux values would result in pixels reaching their saturation level yielding a full white color. The final correlation, as shown in Fig. 6, should be valid for values approximately up to 8000 kWm^{-2} , and therefore, the peak flux density obtained and stated later in the section is about 88% of the saturation point. Upon completion of the calibration, measurements taken using the HFG were plotted with those measured using the CMOS camera at different radial positions, and can be seen in Fig. 7. The average percentage error of this verification was found to be 2.9% with a standard deviation of 3.2%, where the deviation between both plots decreased as the flux density values increased, since the effect of the camera's grayscale resolution became much less. This shows a strong agreement between the values obtained using both methods.

Fig. 7 Verification of the grayscale calibration

Fig. 8 Variation of the measured peak flux density and total power for different focal alignments of the bulb

Optical Alignment of Bulb. Optical alignment of the bulb was done in several steps starting the optimization from an initial peak flux density of approximately 3600 kWm^{-2} . One of these steps included adjusting the optical position of the bulb along the focal axis. Asymmetry was not studied here, and therefore, radial displacement of the bulb was not considered. The focal positioning was adjusted by turning a focal-threaded knob that moves the bulb closer to or further away from the reflector vertex. Each full rotation (360 deg) of this knob provides a focal displacement of approximately 1.6 mm (sixteenth of an inch). The zero reference (0 mm) is the position of the bulb after initial placement inside the simulator and based on the manual alignment guidelines of the solar simulator's manufacturer. Focal position of the bulb was adjusted in increments of 45 deg or 90 deg. Alignment of the bulb can be optimized with respect to maximum power or maximum flux, at the focal plane. In this study, maximum achievable flux value is aimed at, providing optimum flux distribution for our applications (i.e., solar cavity receiver). Once an optimum adjustment was chosen, the optical alignment of the bulb proceeded to a different step by adjusting another parameter. Figure 8 shows one of the intermediate steps for adjusting the focal position of the bulb. The trends in this plot are comparable with the observations made by Rowe et al. [32]. Especially, the trend for total power agrees very well with their findings. Although it has not been shown in this study, it is assumed that displacement of the bulb in the opposite direction would yield the same bell shape as in Ref. [32]. The optimum adjustment was determined to be a focal displacement of 1.8 mm based on the highest obtained peak flux density. The peak flux density increased from a value of approximately 3850 kWm^{-2} to 4200 kWm^{-2} . Upon the final optimization, the peak flux density increased to 6990 kWm^{-2} while the total power increased to 3490 W.

Heat Flux Distribution. The heat flux distribution of the solar simulator was first performed for the maximum supply current of 200 A. A two-dimensional color map on a $10 \times 10 \text{ cm}^2$ target is shown in Fig. 9. The flux distribution can closely be described by a Lorentzian distribution having a peak flux density of $6990 \pm 220 \text{ kWm}^{-2}$ (95%) and a total power on a $10 \times 10 \text{ cm}^2$ target of $3.49 \pm 0.11 \text{ kW}$. Thus, the solar simulator has an electrical-to-radiative power efficiency of 34.9% based on the intercepted power on a $10 \times 10 \text{ cm}^2$ target. The half width defines the radial distance from the center of the flux distribution at which the irradiance drops to half its peak value and was determined to

be 6.25 mm. The half power defines the radial distance at which half of the power is contained and was determined to be 18 mm. Variation of the local flux density, average flux density, and the cumulative power with respect to the radial distance is shown in Fig. 10. The average irradiance on a circular target with a radius of 5 cm was determined as 422 kWm^{-2} , which results in maximum blackbody stagnation temperature of around 1650 K.

Time Response of High Flux Solar Simulators. Temporal measurements were made to assess the output time response of the solar simulator. From the data, conclusions can be drawn on the warm-up time that would be required to reach steady operating conditions. The time response is quantified through observation of the flux density and total power on a $10 \times 10 \text{ cm}^2$ target area. Flux density is measured at two different locations, one being the center of the distribution while the other measures flux density at 5 mm below this center point. For these measurements, the results are taken from the correlated images obtained by the CMOS camera. This rules out the temporal behavior of the heat gauge sensor.

Fig. 9 Two-dimensional view of the measured flux map on a $10 \times 10 \text{ cm}^2$ target area, and at a HFSS input current of 200 A, where centered concentric circles are shown having radii of 0.25, 0.5, 0.75, 1, 2, and 4 cm

Fig. 10 Local flux density, average flux density, and cumulative power as a function of radial distance from the target center at a HFSS input current of 200 A

Fig. 11 Startup time response of the HFSS showing three parameters normalized with respect to their values 60 min after startup, with error bars presenting standard deviation of each data point

454 All three parameters are normalized with respect to their steady
455 values 60 min after startup. The measurements are shown in
456 Fig. 11 and depict comparable results reported in Ref. [26]. The
457 critical time period is during the first 5 min after startup where all
458 three values reach approximately 95% of their final value. More
459 steady behavior is observed after 10 min where the normalized
460 values fluctuate between 96% and 98% of their steady-state value.
461 From this, it can be concluded that a warm-up time of 10–15 min
462 is sufficient to reach steady operating conditions.

463 **Adjustment of Current and Power.** The current supplied to
464 the Xenon arc bulb was varied within the range of 120–200 A
465 with increments of 5 A, to characterize the solar simulator at dif-
466 ferent power levels. Through the control of current supplied, the
467 power received on a target or test object of interest can be varied
468 as desired, which should enable mimicking the sun’s direct normal
469 irradiance throughout the day. The peak flux and total power

on a 10 × 10 cm² target with respect to the supplied current are
shown in Fig. 12. Linear regressions were then performed for
each variable with their respective equations and R^2 values shown
to provide a method of modeling these two parameters and adjust-
ing the current supplied as necessary. In addition, Fig. 13 shows
the relationship between the peak flux density and power, where
almost a perfectly linear relationship exists between these two
values based on its R^2 value. This, in addition to analyzing the
obtained flux distributions at different currents, shows that varying
the current supplied to the bulb does not affect the overall heat
flux distribution. It rather influences the distribution in a linear
and uniform manner.

Effect of the Number of Images Captured. The number of
images captured by the CMOS can affect the results of the experi-
mental determination of heat flux distribution. To determine a
minimum threshold for the number of images to be captured, a

Fig. 12 Peak flux density and total power as a function of electrical input current to the HFSS, with error bars presenting standard deviation on y-axes and uncertainty on x-axis

Fig. 13 Linear correlation between measured peak flux density and total power, with error bars presenting standard deviation

sensitivity analysis was performed comparing the RMSE values of the total power, peak flux, and maximum deviation at any point with respect to the number of images captured. This sensitivity analysis was performed for two different currents of 120 and 200 A to determine whether the threshold for the captured images is affected by instabilities in the arc due to lower current values. Both of the analyses performed are shown in Fig. 14, where the peak flux results were omitted to better visualize the results and since they had similar trend as shown by the maximum deviation. As it is seen in Fig. 14, the RMSE values for the two different parameters exhibit an inversely proportional behavior, which levels off as the number of images increased. Based on that, it can be concluded that the threshold for the number of images captured is around the 30 images mark for a current of 200 A and 25 for a current of 120 A, where the reduction in the RMSE becomes insignificant. This threshold mark is slightly lower than the values of images captured in the literature, where the number of images

captured is around 30–40 images [8,14]. However, as expected, when the number of captured images increase, the RMSE values become slightly lower. Therefore, 100 images were captured and processed for characterizing the heat flux distribution throughout this paper because the time constraint was not a factor to overcome the additional capturing and processing time, which takes approximately three extra minutes.

As the current supplied to the bulb decreases from 200 A to 120 A, the Xenon arc is expected to become more unstable especially below the 80% level of the nominal current of the bulb [33]. In efforts to numerically examine any effects due to the expected instabilities within the arc at lower supply current values, the RMSE values are compared for the two different current values. The RMSE values at a single captured image for total power and maximum deviation were 0.38% and 1.35% for 200 A as compared to 0.13 and 0.50% for 120 A. Based on the RMSE values at the two different current values,

Fig. 14 Sensitivity analysis on the number of captured images based on RMSE values at (a) 200 A and (b) 120 A, with error bars presenting standard deviation

no direct effect was noticed due to the instabilities of the Xenon arc on the parameters investigated, but rather it was noticed that the HFSS's output seemed to be more stable at lower current values. This observation also seems to agree with the results shown in Fig. 12, where the standard deviation of the values seen were significantly lower at lower current values. This could potentially mean that the Xenon arc shows no instabilities at current values as low as 60% of its nominal value.

Determination of the Temporal Instability. The temporal instability of the heat flux obtained at the focal plane was then calculated using Eq. (6) throughout a time span of 6 min. Temporal instability values were averaged out with respect to radial distance from the target's center to smooth out the relationship between the temporal instability and radial position. This relationship is plotted and shown in Fig. 15, where it can also be noticed that the temporal instability in addition to the measurement uncertainty would certainly cause the HFSS to be considered as running at steady operating conditions after 10 min based on the results shown in Fig. 11. The temporal instability seemed to increase at distances further away from the center within the heat flux distribution obtained. The solar simulator can be classified as class A for photovoltaic testing as identified by ASTM and IEC because the temporal instability values were all below 2% for circular areas with radii up to 50 mm.

Determination of the Radial Nonuniformity. The RNU was calculated in a similar manner to the temporal instability using Eq. (5) to represent the relationship between the nonuniformity and radial distance from the center. This is shown in Fig. 16, where it can be seen that the RNU increases with an increasing radial distance up to approximately 8 mm since the flux density distribution's gradient is highest at those locations. Therefore, any slight misalignment in the HFSS will show amplified RNU values. As the radial distance continues to increase, measurement uncertainties and the resolution of the camera have a much more significant effect role in fluctuating the results which in return causing an increasing trend in RNU. Based on the values obtained across the total area of $10 \times 10 \text{ cm}^2$ target, the radial uniformity of the flux distribution is satisfactory within the first 40 mm approximately, where RNU values lie within 10%, but becomes significantly less uniform further away from the center.

The RNU can be attributed to manufacturing imperfections within critical components, mainly the ellipsoidal reflector. These imperfections are usually to be expected in most solar simulators. However, for this simulator, the adjustment mechanism of the bulb also played a significant role in the increased RNU. The mechanism for the bulb's horizontal and vertical positions did not allow for a precise motion of the bulb since it was manually moved by hand. In addition, the mechanism did not allow motion in explicitly one axis, which made the optimization of the simulator, and hence made the observation of more radial uniform distribution much harder.

Fig. 15 Averaged temporal instability for given radial positions

Fig. 16 Radial nonuniformity as a function of radial position

Uncertainty of the Measurements. There are several experimental sources of error that were examined to ensure that the data are reliable and any conclusions stated based on the experimental results are valid. The first source of error can be attributed to the equipment used in measuring the heat flux values directly in order to correlate the grayscale values to heat flux density. The HFG has an accuracy of $\pm 3\%$, which creates a maximum uncertainty of $\pm 210 \text{ kWm}^{-2}$ for the peak flux density. Another source of error is the resolution of the CMOS camera, which has a grayscale range up to 255. Based on this grayscale range and scale factor, the uncertainty stems from the CMOS camera is $\pm 15.78 \text{ kWm}^{-2}$. In addition, the data acquisition system used has an uncertainty of $\pm 4.7 \mu\text{V}$, which corresponds to an uncertainty of $\pm 2.315 \text{ kWm}^{-2}$. These uncertainty values were used to calculate a single weighted uncertainty value for the linear regression of the grayscale values that was used for acquiring the experimental results. Using the aforementioned uncertainty values, in addition to any uncertainty that arises due to the process unsteadiness, the uncertainty of all measurements can be calculated using the method defined by the American National Standard Institute (ANSI) [34]. In accordance

to this, the uncertainty in the determined peak flux is, as also stated earlier, $\pm 220 \text{ kWm}^{-2}$ with 95% confidence.

Image Merging Process. The resulting flux map obtained by merging five overlapping flux measurements through the *merging method* shown in Fig. 17. The contour map is shown in Fig. 18. The peak flux density of the bivariate distribution was found to be 6947 kWm^{-2} . This differs by 0.7% from the heat flux density obtained with the regular mapping method. Similarly, the total power incident on a $10 \times 10 \text{ cm}^2$ area was determined as 3.73 kW which corresponds to a deviation of 6.5%. Per this method, the CMOS camera was repositioned in order to fit the whole Lambertian target area inside the image frame rather than just a quarter (Fig. 1). This deviation is due to additional uncertainties by considering a larger target size but primarily caused by the affected resolution of the grayscale images. The resolution was computed by quantifying the amount of pixels representing the observed area in mm^2 in the untransformed image. The resolution was calculated as 8 px/ mm^2 for the captured images of the *merging*

Fig. 17 Three-dimensional flux distribution on a $30 \times 30 \text{ cm}^2$ target area obtained through merging of five flux maps, and at a HFSS input current of 200 A

Fig. 18 Two-dimensional view of the measured flux map on a $10 \times 10 \text{ cm}^2$ target area obtained using the merging method, and at a HFSS input current of 200 A, where centered concentric circles are shown having radii of 0.25, 0.5, 0.75, 1, 2, and 4 cm

method. For the regular mapping method, the resolution was calculated as 36 px/mm^2 . This clearly indicates superior accuracy of the regular method and explains the slightly higher deviation on the total flux between both methods.

It can be seen in Fig. 17 that the flux density was quantified up to a radius of 10 cm. Beyond this radius, processing of the grayscale images did not yield any flux density values. The reason for this is that the calibration of the grayscale values and the corresponding heat flux as depicted in Fig. 6 is constrained by the 8-bit grayscale integer value. In other words, the range of obtainable flux density values up to approximately 8000 kWm^{-2} correlates to the range of 256 grayscale values. As aforementioned for the calibration, the applied correlation should account for saturation once higher flux values would be observed. This then leads to

unclear distinction of the grayscale values close to 0 (black) in the tail of the flux distribution where values fluctuate between 0 and 1.

Figure 19 depicts the flux density, both local and average, and the cumulative power of the merged flux map. The cumulative power at a radius of 5 cm equals to 3.5 kW which differs by approximately 0.1 kW from the values obtained with the regular heat flux mapping method (Fig. 10). The total cumulative power for the obtained values within the radius of 10 cm was found to be 4.40 kW.

Based on these results, it can be implied that the largest portion of incident radiative power at the focal plane falls within the circular area with 10 cm radius, and thus encompasses an area larger than the area of interest. However, the *merging method* seems to be a promising approach for the characterization of wider flux distributions, e.g., parabolic concentrators.

Conclusion and Future Work

In this paper, an indirect heat flux mapping of a new 10 kW_e HFSS for solar thermal applications is presented. The method applied comprises the calibration of a CMOS camera with heat gauge data obtained. Compared to most other methods, this method uses only one Lambertian target. This removes misalignment errors, which would otherwise occur when interchanging the targets and would as well save an additional cost and time. The heat flux maps obtained at maximum power depicted a peak flux density of 6690 kWm^{-2} with a total power of 3.49 kW incident on a $10 \times 10 \text{ cm}^2$ square target size. Variation of the power supply current showed to have no effect on the overall heat flux distribution other than a linear and uniform increase or decrease of the flux. The results of a sensitivity analysis on the number of images captured by the CMOS camera concluded that the threshold for stable and repeatable data was 30 images. The new method presented would enable to acquire incident flux data on larger target sizes. Although the resolution of the raw grayscale images in this method was significantly lower than then original method, the resulting peak flux density deviated just by 0.7% while the total power on the same target size of $10 \times 10 \text{ cm}^2$ differed by 6.5%. The method was predicted to be favorable for wider flux distributions in the field of concentrated solar power.

Fig. 19 Local flux density, average flux density, and cumulative power as a function of radial distance from the target center at a HFSS input current of 200 A obtained using the merging method

Our future work in heat flux measurements and characterization of solar simulators includes further analysis and characterization of the Xenon arc as the radiation source. Parallel heat flux distributions from the bulb were collected at different focal planes and distances from the simulator for distances up to 6.4 cm behind the focal plane in a future attempt to implement an inverse ray tracing from the obtained flux distributions back to the Xenon arc. The preliminary results show significant drops in the peak flux densities obtained behind the focal plane, where the peak flux reduced from 6990 to 2250 kWm^{-2} at a distance of 4.8 cm. The objective from the inverse ray tracing is to obtain the directional characteristics of the Xenon arc in a direct experimental method, rather than relying on forward ray tracing simulations.

Acknowledgment

This research has been funded by University of Minnesota Duluth. Authors appreciate Dr. Matthew Lindemer's contribution in conducting some portion of the literature survey. The corresponding author appreciates the diligent effort and support of Professor Aydin Durgunoglu, Professor Rudy Perrault, Ms. Kathleen Adee, and Mr. Michael Swanson in materialization of High Flux Gas Dynamics Laboratory.

Nomenclature

c = geometric coefficient
 M_i = measured value
 $\bar{M}$ = mean of measured values
 N = total number of measurements
 q'' = heat flux, W m^{-2}
 RMSE = root-mean-square error, %
 T = transformation matrix
 T_{bs} = blackbody stagnation temperature, K
 TI = temporal instability, %
 σ = Stefan Boltzmann constant, $\text{Wm}^{-2} \text{K}^{-4}$

References

- [1] Ekman, B. M., Brooks, G., and Rhamdhani, M. A., 2016, "Development of High Flux Solar Simulators for Solar Thermal Research," *Energy Technol.*, **141**(1), pp. 149–159.
- [2] Gallo, A., Marzo, A., Fuentealba, E., and Alonso, E., 2017, "High Flux Solar Simulators for Concentrated Solar Thermal Research: A Review," *Renew. Sustainable Energy Rev.*, **77**, pp. 1385–1402.

- [3] Dong, X., Sun, Z., Nathan, G. J., Ashman, P. J., and Gu, D., 2015, "Time-Resolved Spectra of Solar Simulators Employing Metal Halide and Xenon Arc Lamps," *Sol. Energy*, **115**, pp. 613–620.
- [4] Petrasch, J., et al., 2007, "A Novel 50 kW 11,000 Suns High-Flux Solar Simulator Based on an Array of Xenon Arc Lamps," *ASME J. Sol. Energy Eng.*, **129**(4), pp. 405–411.
- [5] Siegel, N. P., Drive, D., Roba, J. P., and Drive, D., 2018, "Design, Modeling, and Characterization of a 10kW_e Metal Halide High Flux Solar Simulator," *ASME J. Sol. Energy Eng.*, **140**, pp. 1–7.
- [6] Wang, W., Aichmayer, L., Garrido, J., and Laumert, B., 2017, "Development of a Fresnel Lens Based High-Flux Solar Simulator," *Sol. Energy*, **144**, pp. 436–444.
- [7] Gill, R., Bush, E., Haueter, P., and Loutzenhiser, P., 2015, "Characterization of a 6 kW High-Flux Solar Simulator With an Array of Xenon Arc Lamps Capable of Concentrations of Nearly 5000 Suns," *Rev. Sci. Instrum.*, **86**(12), 121101.
- [8] Leveque, G., Bader, R., Lipinski, W., and Haussener, S., 2016, "Experimental and Numerical Characterization of a New 45 kW_e Multisource High-Flux Solar Simulator," *Opt. Express*, **24**(22), pp. 1360–1373.
- [9] Martinez-Manuel, L., et al., 2018, "A 17.5 kW_e High Flux Solar Simulator With Controllable Flux-Spot Capabilities: Design and Validation Study," *Sol. Energy*, **170**(1), pp. 807–819.
- [10] Ophoff, C., Korotunov, S., and Ozalp, N., 2017, "Optimization of Design and Process Parameters for Maximized and Stable Solar Receiver Efficiency," *Second Thermal and Fluid Engineering Conference*, **1**, Paper No. TFEC-IWHT2017-18225.
- [11] Kuhn, P., and Hunt, A., 1991, "A New Solar Simulator to Study High Temperature Solid-State Reactions With Highly Concentrated Radiation," *Sol. Energy Mater.*, **24**(1–4), pp. 742–750.
- [12] Li, J., Gonzalez-Aguilar, J., Pérez-Rábago, C., and Zeaiter, H., 2014, "Optical Analysis of a Hexagonal 42kW_e High-Flux Solar Simulator," *Energy Procedia*, **57**, pp. 590–596.
- [13] Wieghardt, K., et al., 2016, "SynLight—The World's Largest Artificial Sun," *AIP Conference Proceedings*, Vol. 1734, **1**, p. 030038.
- [14] Sarwar, J., Georgakis, G., LaChance, R., and Ozalp, N., 2014, "Description and Characterization of an Adjustable Flux Solar Simulator for Solar Thermal, Thermochemical and Photovoltaic Applications," *Sol. Energy*, **100**, pp. 179–194.
- [15] Gomez-Garcia, F., Gonzalez-Aguilar, J., and Romero, M., 2011, "Experimental 3D Flux Distribution of a 7 kW_e Solar Simulator," *SolarPACES Conference*, **1**, p. 1.
- [16] Alonso, E., and Romero, M., 2015, "A Directly Irradiated Solar Reactor for Kinetic Analysis of Non-Volatile Metal Oxides Reductions," *Int. J. Energy Res.*, **39**(9), pp. 1217–1228.
- [17] Gokon, N., Takahashi, S., Yamamoto, H., and Kodama, T., 2008, "Thermochemical Two-Step Water-Splitting Reactor With Internally Circulating Fluidized Bed for Thermal Reduction of Ferrite Particles," *Int. J. Hydrogen Energy*, **33**(9), pp. 2189–2199.
- [18] Haueter, P., Seitz, T., and Steinfeld, A., 2016, "A New High-Flux Solar Furnace for High-Temperature Thermochemical," *ASME J. Sol. Energy Eng.*, **121**(1), pp. 77–80.
- [19] Krueger, K., Davidson, J. H., and Lipinski, W., 2011, "Design of a New 45 High-Flux Solar Simulator for High-Temperature Solar Thermal and Thermochemical Research," *ASME J. Sol. Energy Eng.*, **133**(1), p. 1.

- AQ15 725
726
727
728
729
730
731
732
733
734
735
736
- AQ16 736
- [20] Erickson, B. M., 2012, "Characterization of the University of Florida Solar Simulator and an Inverse Solution for Identifying Intensity Distributions From Multiple Flux Maps in Concentrating Solar Applications," Master thesis, ■, ■.
- [21] Moss, R. W., Shire, G. S. F., Eames, P. C., Henshall, P., Hyde, T., and Arya, F., 2018, "Design and Commissioning of a Virtual Image Solar Simulator for Testing Thermal Collectors," *Sol. Energy*, **159**, pp. 234–242.
- [22] Esen, V., Sa, Ş., and Oral, B., 2017, "Light Sources of Solar Simulators for Photovoltaic Devices: A Review," *Renew. Sustain. Energy Rev.*, **77**, pp. 1240–1250.
- [23] Krueger, K. R., Lipiński, W., and Davidson, J. H., 2013, "Operational Performance of the University of Minnesota 45 kWe High-Flux Solar Simulator," *ASME J. Sol. Energy Eng.*, **135**(4), p. 044501.
- [24] ASTM, 2005, *Standard Specification for Solar Simulators for Photovoltaic Testing*, ASTM International, West Conshohocken, PA, Standard No. ASTM-E927-05.
- [25] IEC, 2007, "International Electrotechnical Commission Standard for Solar Simulator Performance Requirements," ■, ■, Standard No. IEC-60904-9.
- [26] Krueger, K. R., 2012, "Design and Characterization of a Concentrating Solar Simulator," ■.
- [27] IREM SpA, 2018, "Installation and Operational Manual: EX-200GM3," ■.
- [28] Ballestrin, J., Ulmer, S., Morales, A., Barnes, A., Langley, L. W., and Rodríguez, M., 2003, "Systematic Error in the Measurement of Very High Solar Irradiance," *Sol. Energy Mater. Sol. Cells*, **80**(3), pp. 375–381. 737 738
- [29] Ballestrin, J., Estrada, C. A., Rodríguez-Alonso, M., Pérez-Rábago, C., Langley, L. W., and Barnes, A., 2006, "Heat Flux Sensors: Calorimeters or Radiometers?," *Sol. Energy*, **80**, pp. 1314–1320. 739 740
- [30] Guillot, E., Alxneit, I., Ballestrin, J., Sans, J. L., and Willsh, C., 2014, "Comparison of 3 Heat Flux Gauges and a Water Calorimeter for Concentrated Solar Irradiance Measurement," *Energy Procedia*, **49**, pp. 2090–2099. 741 742
- [31] Schwarz, B., Ritt, G., Koerber, M., and Eberle, B., 2017, "Laser-Induced Damage Threshold of Camera Sensors and Micro-Optoelectromechanical Systems," *Opt. Eng.*, **56**(3), ■. 743 744
- [32] Rowe, S. C., et al., 2017, "Experimental Evidence of an Observer Effect in High-Flux Solar Simulators," *Sol. Energy*, **158**, pp. 889–897. 745
- [33] Lighting, S., 2017, "Xenon 10,000 Solar Simulator," ■.
- [34] ANSI/NCSL, 1997, "American National Standard for Expressing Uncertainty—U.S. Guide to the Expression of Uncertainty in Measurement," ■, Standard No. ANSI/NCSL-Z540-2-1997. 746 747

Author Proof