Arbitrary high-order extended ENO schemes for hyperbolic conservation laws

Chunguang Xu^{a,b}, Fan Zhang^{c,*}, Haibo Dong^d, Hang Jiang^e

^a*School of Aeronautics and Astronautics, Sun Yat-sen University, Guangzhou 510006, China*

^b*State Key Laboratory of Aerodynamics, China Aerodynamics Research and Development Center, Mianyang, China*

^c*Centre for mathematical Plasma-Astrophysics, Department of Mathematics, KU Leuven, Celestijnenlaan 200B, 3001 Leuven, Belgium*

^d*Beijing Institute of Space Mechanics and Electricity, China Academy of Space Technology, Beijing 100094, China*

^e*COMAC Shanghai Aircraft Design and Research Institute, Shanghai 201210, China*

Abstract

Achieving high numerical resolution in smooth regions and robustness near discontinuities within a unified framework is the major concern while developing numerical schemes solving hyperbolic conservation laws, for which the essentially non-oscillatory (ENO) type scheme is a favorable solution. Therefore, an arbitrary-high-order ENO-type framework is designed in this paper. With using a typical five-point smoothness measurement as the shock-detector, the present schemes are able to detect discontinuities before spatial reconstructions, and thus more spatial information can be exploited to construct incremental-width stencils without crossing discontinuities, ensuring ENO property and high-order of accuracy at the same time. The present shock-detection procedure is specifically examined for justifying its performance of resolving high-frequency waves, and a standard metric for discontinuous solutions is also applied for measuring the shock-capturing error of the present schemes, especially regarding the amplitude error in post-shock regions. In general, the present schemes provide high-resolution, and more importantly, the schemes are more efficient compared with the typical WENO schemes since only a five-point smoothness measurement is applied for arbitrary-high-order schemes. Numerical results of canonical test cases also provide evidences of the overall performance of the present schemes.

Keywords: arbitrary-high-order; ENO; shock-detector; computational efficiency; shock-capturing

1. Introduction

The essentially non-oscillatory (ENO) scheme [1] and the weighted essentially non-oscillatory (WENO) scheme [2] are popular nonlinear finite difference methods solving hyperbolic partial differential equations (PDEs), and these two methods also provide fundamental principles for constructing novel high-order shock-capturing schemes. An essential part of WENO schemes is utilising all the candidate stencils by a convex combination which is based on a nonlinear weighting strategy, to provide a high-order reconstruction which is free from spurious oscillations in shock-capturing computations. WENO-type schemes approximately recover the underlying linear schemes if discontinuities are deemed to be vanished, according to their smoothness measurements, thus resulting in high-order of accuracy

*Corresponding author.

Email address: fan.zhang@kuleuven.be, zhang.f@gmx.com (Fan Zhang)

in smooth regions. **In the meantime, the contribution of oscillating (sub)stencils** is approximately eliminated by decreasing the corresponding nonlinear weights, since those stencils are likely to be crossing discontinuities.

Specifically, the WENO scheme using the JS weight [3] provides robust shock-capturing capability in a wide range of physical and engineering problems [4, 5], and the WENO-Z scheme [6] introduces a global smoothness indicator **and is of higher spatial accuracy, especially at smooth critical points [6, 7]. Numerous numerical results suggest that** the smoothness-measurement methods [3, 6] are essential for improving the overall performance of ENO-type schemes [8, 6, 7, 9, 10]. **Moreover, the shock-detection procedure is essential for hybrid high-order finite-difference schemes [11, 12, 13]. In fact, the idea of hybrid schemes is straightforward and effective. As long as the shock waves/discontinuities are accurately detected, high-resolution schemes can be applied for resolving smooth wave structures without complex nonlinear shock-capturing algorithms, significantly reducing the computational effort. For instance, recently, Zhao et al. [13] have designed a WENO-based shock detector which shows excellent performance while constructing a seventh-order hybrid compact-upwind/WENO scheme. The shock-detector can also be used to adaptively change the parameter of a shock-capturing scheme [14].**

Despite the success of these high-order schemes, in order to increase the order of accuracy of a specific numerical scheme, usually, more degree-of-freedom (DOFs) are necessary for constructing higher-order polynomials, and thus more computational effort is inevitable. For finite difference schemes, including WENO schemes [15, 16, 7] and WCNSs [17, 18, 19], DOFs are increased by extending the candidate stencil(s). Balsara and Shu proposed a class of numerical schemes [15] that are higher-order extensions of the WENO-JS scheme [3]. Their methods, which combine with the monotonicity preserving bounds of Suresh and Huynh [20], were named as MPWENO schemes. Up to seventeenth-order WENO schemes were developed by Gerolymos et al. [16]. As shown in these articles, obviously, more complicated smoothness indicators are inevitably required for measuring the smoothness of wider candidate stencils and calculating the corresponding nonlinear weights [16, 7], and thus those higher-order schemes are, unsurprisingly, computationally more expensive compared with typical fifth-order schemes.

Zhao et al. [21] proposed a standard metric to evaluate the overall performance of high-order finite difference schemes, with taking the computational efficiency into account. Since the seventh-order WENO scheme requires almost 50% more CPU time than the fifth-order WENO scheme [21], higher-order schemes may need similar CPU time as that of the fifth-order scheme, for achieving moderate numerical error on given (relatively) coarser meshes. Of course, if high accuracy is expected on fine meshes, higher-order schemes still are **the more suitable choice** since they converge faster than lower-order schemes [22]. In general, no doubt, further improving the efficiency of these nonlinear shock-capturing schemes is a crucial issue [23, 24, 25]. Therefore, an idea first sketched in Ref. [26] and extended by Zhang et al. [27] is further developed and analyzed in this work, in order to reduce the overall computational effort of high-resolution solutions.

In this paper, we manage to use the smoothness measurement of typical five-point schemes as the shock-detector, providing locations of all the discontinuities in computation domains, and allowing arbitrary high-order spatial reconstructions on smooth fields, as long as the smooth regions are large enough for the stencils on which high-order polynomials are defined. Therefore, the computational cost of complicated smoothness measurements may be **avoid-**

ed. The remainder of this paper is organized as follows. In the next section, some fundamental formulas are introduced, and then the present method is introduced in detail in section 3. In section 4, the spectral properties and the shock-capturing capability are investigated by several analyzing techniques, and in section 5, canonical numerical test cases are used to further evaluate the present method. Eventually, concluding remarks are given in the last section.

2. Fundamentals

The one-dimensional scalar hyperbolic conservation law, i.e.

$$\frac{\partial u}{\partial t} + \frac{\partial f(u)}{\partial x} = 0, \quad (1)$$

is used to explain and examine the present scheme eventually solving hyperbolic system of equations. In Eq. (1) the characteristic velocity is $\frac{\partial f(u)}{\partial u}$ and assumed to be positive, without loss of generality, and then the spatial discretization of Eq. (1) is given on an equally spaced grid, leading to an ODE (ordinary differential equation) system, i.e.

$$\frac{du_i}{dt} = -\frac{\partial f}{\partial x}|_{x=x_i}, \quad i = 1, \dots, n. \quad (2)$$

The partial derivatives in x -direction are approximated by using the finite difference formula, i.e.

$$\frac{du_i}{dt} = -\frac{1}{\Delta x}(h_{i+1/2} - h_{i-1/2}). \quad (3)$$

The flux function $h_{i\pm 1/2}$ at half points can be implicitly defined by

$$f(x) = \frac{1}{\Delta x} \int_{x-\Delta x/2}^{x+\Delta x/2} h(\xi) d\xi, \quad (4)$$

and the semi-discretized form can be written as

$$\frac{du_i}{dt} \approx -\frac{1}{\Delta x}(\hat{f}_{i+1/2} - \hat{f}_{i-1/2}). \quad (5)$$

Without using the concept of "convex combination" for approximating the numerical flux function $\hat{f}_{i\pm 1/2}$, predefined linear high-order reconstructions can be given as an unified form, i.e.

$$h(x) \approx \hat{f}(x) = \sum_{m=i-l}^{i+r} a_m f_m, \quad (6)$$

where l and r define the amount of the grid points used in high-order spatial reconstructions. By appropriately defining the right hand side of Eq. (6), high-order oscillation-free spatial approximation can be achieved, and more details of the unified formula is to be introduced in the following sections.

As a default solution, the local Lax-Friedrichs scheme is used for flux splitting in this work, and for solving Euler equations the classical characteristic decomposition at grid points [1] is utilized for calculating the f_m in Eq. (6). Eventually, after calculating the right hand side of the ODE system, i.e. Eq. (2), the temporal differential term can be solved by using the third-order strongly stable Runge-Kutta method [28], of which the detailed formula is omitted here for simplicity.

Table 1: The coefficients of the numerical flux functions of the present schemes.

$\hat{f}_{i+1/2}$	a_{i-4}	a_{i-3}	a_{i-2}	a_{i-1}	a_i	a_{i+1}	a_{i+2}	a_{i+3}	a_{i+4}
$\hat{f}_{0,i+1/2}$	1/630	-41/2520	199/2520	-641/2520	1879/2520	275/504	-61/504	11/504	-1/504
$\hat{f}_{1,i+1/2}$	0	-1/280	29/840	-139/840	533/840	533/840	-139/840	29/840	-1/280
$\hat{f}_{2,i+1/2}$	1/280	-9/280	113/840	-307/840	743/840	365/840	-11/168	1/168	0
$\hat{f}_{3,i+1/2}$	0	-1/140	5/84	-101/420	319/420	107/210	-19/210	1/105	0
$\hat{f}_{4,i+1/2}$	0	0	1/60	-2/15	37/60	37/60	-2/15	1/60	0
$\hat{f}_{5,i+1/2}$	0	-1/60	7/60	-23/60	19/20	11/30	-1/30	0	0
$\hat{f}_{6,i+1/2}$	0	0	1/30	-13/60	47/60	9/20	-1/20	0	0
$\hat{f}_{7,i+1/2}$	0	0	0	-1/12	7/12	7/12	-1/12	0	0
$\hat{f}_{8,i+1/2}$	0	0	1/12	-5/12	13/12	1/4	0	0	0
$\hat{f}_{9,i+1/2}$	0	0	0	0	1/3	5/6	-1/6	0	0
$\hat{f}_{10,i+1/2}$	0	0	0	-1/6	5/6	1/3	0	0	0
$\hat{f}_{11,i+1/2}$	0	0	1/3	-7/6	11/6	0	0	0	0

3. The present method

In this section, the details of the present method are introduced. The high-order linear candidate reconstructions are introduced in the first subsection. These linear reconstructions can be applied as long as the discretized solutions are smooth. A shock-detection procedure is then introduced for detecting discontinuities and providing information of the smooth fields. Finally, in the last subsection the algorithms combining the linear candidate reconstructions in the (numerically) given smooth regions are introduced.

3.1. High-order reconstruction

As shown in the previous section, we still need to define the high-order spatial approximation in Eq. (6) to eventually solve the hyperbolic conservation laws. In this subsection, up to ninth-order linear candidate reconstructions of the numerical flux evaluated at $x_{i+1/2}$ are given as the basic building blocks for constructing high-order schemes in this work, and higher-order schemes are also achievable by following the present idea. Here, the unified form of these candidate reconstructions is

$$\hat{f}_{i+1/2} = \sum_{m=i-4}^{i+4} a_m f_m, \quad (7)$$

and the coefficients of the optimal linear reconstructions are given in Table 1. It shall be noted that, with using the symmetrical form of the present scheme, the approximation for $\hat{f}_{i-1/2}$ can be given straightforwardly.

Obviously, if a computation domain is without any discontinuity, the ninth-order linear reconstruction can be applied in the whole domain (theoretically arbitrary-high-order methods can be applied). If a discontinuity makes the smooth region smaller, lower-order reconstructions are still usable. Therefore, by **appropriately selecting the linear candidate reconstructions, high-order of accuracy can be easily achieved.** In fact, the selection procedure combining the linear candidate reconstructions is similar to the idea of hybrid schemes, which typically integrate a shock-capturing scheme and a high-resolution scheme. Usually, the WENO-type schemes can be used for the shock-capturing computation of a hybrid scheme [11, 13], as WENO-type schemes are robust and of high-order accuracy. However, the present method is the combination of linear reconstructions, and the shock-capturing performance can be ensured by avoiding any reconstruction across discontinuity.

3.2. Shock-detection

After providing the candidate high-order reconstructions in the previous subsection, the question still needs to be answered is straightforward: how to find out (the locations of) the discontinuities in the computation domain. It is worth noting that, various state-of-the-art techniques can be used to serve this purpose. For instance, the boundary-variation-diminishing (BVD) algorithm [29] has been used to achieve arbitrary-high-order spatial reconstructions [30, 31], showing high-resolution and robust shock-capturing capability. The nonlinear weights of WENO schemes have also been used to design the switch function which indicates the locations of discontinuities [24, 13].

The most popular ENO/WENO scheme, i.e. WENO-JS scheme [3], shows robust shock-capturing capability in numerous applications. Therefore, its smoothness measurement itself is suitable for detecting shock waves. Here, the smoothness measurement of the fifth-order WENO-JS scheme [3] is used to find out the locations of discontinuities, including shock wave and contact discontinuity, for all the present schemes to be introduced in the following paragraphs. It is worth noting that the present fifth-order scheme will thus have no efficiency advantage, and it will be only used as a reference scheme, to show the advantages of the present seventh- and ninth-order schemes.

Here, the smoothness measurement is first given as

$$\gamma_k = \frac{d_k}{(\beta_k + \varepsilon)^2}, \quad k = 0, 1, 2, \quad (8)$$

where β_k , ε and d_k are all defined the same as those of the fifth-order WENO-JS scheme [3]. More specifically, the d_k are

$$d_0 = 0.1, \quad d_1 = 0.6, \quad d_2 = 0.3, \quad (9)$$

following from the optimal linear weights of the WENO-JS scheme, and $\varepsilon = 10^{-6}$ is the small value avoiding zero denominator. It should be noted that the small value also acts as a cutoff of the smoothness measurement [32], and has been modified to avoid overwhelming small measurements [6]. For evaluating the numerical flux at $x_{i+1/2}$, the local smoothness indicator β_k should be defined as

$$\begin{aligned} \beta_0 &= \frac{1}{4}(f_{i-2} - 4f_{i-1} + 3f_i)^2 + \frac{13}{12}(f_{i-2} - 2f_{i-1} + f_i)^2, \\ \beta_1 &= \frac{1}{4}(f_{i-1} - f_{i+1})^2 + \frac{13}{12}(f_{i-1} - 2f_i + f_{i+1})^2, \\ \beta_2 &= \frac{1}{4}(3f_i - 4f_{i+1} + f_{i+2})^2 + \frac{13}{12}(f_i - 2f_{i+1} + f_{i+2})^2. \end{aligned} \quad (10)$$

More detailed analysis and discussion about the smoothness measurement can be found in Ref. [3].

Then the smoothness measurement is normalised as

$$\chi_k = \frac{\gamma_k}{\sum_{l=0}^2 \gamma_l}. \quad (11)$$

A cut-off procedure in Ref. [9] can thus be applied, i.e.

$$\delta_k = \begin{cases} 0, & \text{if } \chi_k < C_T, \\ 1, & \text{otherwise,} \end{cases} \quad (12)$$

where $C_T = 10^{-2}$ is used as the default setting in this work for robustness, but the other values are also tested.

Therefore, if a δ_k equals 0, there is a discontinuity **deemed to be** located within the range of the corresponding three-point substencil. Otherwise, the corresponding substencil is deemed to be smooth. Eventually, by calculating this five-point smoothness measurement in the whole computation domain, the discontinuities in the whole computation domain will be detected and given for **the spatial reconstruction procedure**. **It should be further noted that in the present method, the smoothness measurement is only used for shock-detection, and the nonlinear weighting strategy used in the WENO-JS scheme is replaced by the algorithms introduced in the next subsection.**

3.3. Stencil-selection

The shock detection procedure in the previous subsection is defined for all the grid half-points, i.e. $\{x_{i+1/2} | i = 1, \dots, n\}$, and thus the stencils used to define the shock detection procedure are periodically defined in the whole domain including the ghost points of the boundaries, overlapping with each other, as shown in Fig. 1. It is worth noting that for a WENO-type scheme, the smoothness measurements in the whole computation domain are also overlapping in the same manner.

Figure 1: Schematic of the stencils on which the smoothness measurement is defined.

More specifically, a five-point smoothness measurement that includes $\{\beta_{k,i} | k = 0, 1, 2\}$ can be used to provide sufficient local smoothness information to define a fifth-order reconstruction, covering grid points $\{x_m | m = i - 2, i - 1, i, i + 1, i + 2\}$ and evaluating the numerical flux at $x_{i+1/2}$. As for a seventh-order WENO scheme, a seven-point smoothness measurement which involves higher-order polynomials is usually required [15]. However, as shown in Fig. 1, by simply periodically calculating the five-point smoothness measurement, we are able to estimate the smoothness in the whole computation domain, and thus if the smoothness is guaranteed higher-order reconstructions can be applied without using more complicated smoothness measurements. Therefore, while calculating the numerical flux at $x_{i+1/2}$, besides the typical five-point smoothness measurement in the middle box in Fig.1, we can use two neighbour-

ing smoothness measurements to provide sufficient smoothness information on a seven-point stencil, covering grid points $\{x_m | i-3 \leq m \leq i+3\}$, and allowing a seventh-order reconstruction for the numerical flux $\hat{f}_{i+1/2}$. Similarly, in order to cover a nine-point region near $x_{i+1/2}$, five overlapping five-point smoothness measurements are necessary to be involved, for providing the locations of discontinuities at grid points $\{x_m | i-4 \leq m \leq i+4\}$. As mentioned above, the five-point smoothness measurements are periodically defined in the whole domain, and thus the smoothness information can be provided in the whole domain, which means that a higher-order reconstruction can be provided without crossing any discontinuity. Theoretically, arbitrary high-order schemes can be defined in this way, but only up to ninth-order schemes are discussed in this work.

More specifically, the smoothness information needed for fifth-, seventh- and ninth-order schemes are collected as

$$\Delta_i^{5\text{th}} = (\delta_{0,i}, \delta_{1,i}, \delta_{2,i}), \quad (13)$$

$$\Delta_i^{7\text{th}} = (\delta_{0,i-1}, \delta_{0,i}, \delta_{1,i}, \delta_{2,i}, \delta_{2,i+1}), \quad (14)$$

and

$$\Delta_i^{9\text{th}} = (\delta_{0,i-2}, \delta_{0,i-1}, \delta_{0,i}, \delta_{1,i}, \delta_{2,i}, \delta_{2,i+1}, \delta_{2,i+2}), \quad (15)$$

where these data are calculated according to Eq. (12), using the information shown in Fig. 1. Apparently, due to the overlapping manner of the smoothness measurements, the information providing the locations of discontinuities is actually redundant. For example, in Fig.1, $\delta_{1,i}$ and $\delta_{2,i-1}$ cover the same three grid points, viz. x_{i-1} , x_i and x_{i+1} . However, since we only extend the stencil while the central five-point full stencil is completely smooth, the central $\delta_{k,i}$ is preferable. **Details of the algorithms using these information are introduced as follows.**

We define the very simple Algorithms 1, 2 and 3 for the fifth-, seventh- and ninth-order schemes respectively, based on the polynomials in Table 1. **More specifically, in Algorithm 1, we can see that if $\Delta_i^{5\text{th}} = \{1, 1, 1\}$, three three-point substencils are all deemed to be smooth, and thus a fifth-order linear reconstruction can be directly applied. If one of the three-point substencils is deemed to be crossing discontinuity, a lower-order reconstruction is then applied, avoiding utilising the information at grid points having oscillating solutions. Similarly, the seventh-order scheme, i.e. Algorithm 2, first examines the smoothness information at grid points $\{x_m | i-3 \leq m \leq i+3\}$, and then reduces the order of accuracy in case there is at least one substencil crossing discontinuity. The ninth-order scheme is also designed based on the same idea. It can be found that for a higher-order scheme the algorithm only needs to examine more smoothness information in the computation domain, without changing the smoothness measurement.** It should be noted that the present algorithms are defined to show the simple logic of designing a higher-order scheme, which preserves the ENO property since all the oscillatory stencils are excluded in the final spatial reconstruction, and we can further simplify the practical logical statements while programming.

Data: Grid information x_i and flux function f_i at time step n .

Result: Left variables $f_{L,i+\frac{1}{2}}$ at $x_{i+\frac{1}{2}}$.

```

1 begin
2   switch  $\Delta_i^{5th}$  do
3     case{1, 1, 1}  $\hat{f}_{i+1/2} = \hat{f}_{6,i+1/2}$ 
4     case{0, 1, 1}  $\hat{f}_{i+1/2} = \hat{f}_{7,i+1/2}$ 
5     case{1, 1, 0}  $\hat{f}_{i+1/2} = \hat{f}_{8,i+1/2}$ 
6     // * can be either 1 or 0
7     case{*, 0, 1}  $\hat{f}_{i+1/2} = \hat{f}_{9,i+1/2}$ 
8     case{0, 1, 0}  $\hat{f}_{i+1/2} = \hat{f}_{10,i+1/2}$ 
9     case{1, 0, 0}  $\hat{f}_{i+1/2} = \hat{f}_{11,i+1/2}$ 
10  endsw
11 end

```

Algorithm 1: The fifth-order scheme.

4. Evaluation of the schemes

In this section, we use two methods to show the performance of the present high-order schemes in resolving smooth high-frequency waves and capturing discontinuous solutions respectively. Especially, for comparison, the underlying linear upwind schemes and the up to ninth-order WENO schemes with JS nonlinear weights [3] are used as references. Specifically, the local smoothness indicators of the seventh- and ninth-order WENO schemes are defined according to Ref. [7].

4.1. Approximate dispersion relation

The approximate dispersion relation (ADR) analysis [33] is able to show the spectral properties of nonlinear numerical schemes, including the numerical dissipation and dispersion corresponding to different wave-numbers. Therefore, this method is applied to examine the present schemes. More specifically, ADR analysis shows the dissipation and dispersion errors of numerical schemes in wave-number space by solving a linear advection equation with a smooth initial condition (typically a sine wave). A modified wave-number ξ (normalized to lie in the interval $[0, \pi]$) is defined for all modes supported on the given grid, and its real (ξ_R) and imaginary (ξ_I) parts respectively represent dispersion and dissipation properties of the numerical schemes being evaluated.

The results of the present schemes with using the default parameter $C_T = 10^{-2}$ are shown in Fig. 2. Obviously, the classical WENO-JS scheme is relatively more dissipative and dispersive, but higher-order WENO schemes provide significant improvements. The present schemes also show significant advantages compared with the fifth-order WENO scheme. Specifically, in the high-wave-number region the present schemes show better performance, even compared with the seventh- and ninth-order WENO schemes. However, in the intermediate wave-number region the seventh-

Data: Grid information x_i and flux function f_i at time step n .

Result: Left variables $f_{L,i+\frac{1}{2}}$ at $x_{i+\frac{1}{2}}$.

```

1 begin
2   switch  $\Delta_i^{7th}$  do
3     case{1, 1, 1, 1, 1}  $\hat{f}_{i+1/2} = \hat{f}_{3,i+1/2}$ 
4     case{0, 1, 1, 1, 1}  $\hat{f}_{i+1/2} = \hat{f}_{4,i+1/2}$ 
5     case{1, 1, 1, 1, 0}  $\hat{f}_{i+1/2} = \hat{f}_{5,i+1/2}$ 
6     case else          call Algorithm 1.
7   endsw
8 end

```

Algorithm 2: The seventh-order scheme.

Data: Grid information x_i and flux function f_i at time step n .

Result: Left variables $f_{L,i+\frac{1}{2}}$ at $x_{i+\frac{1}{2}}$.

```

1 begin
2   switch  $\Delta_i^{9th}$  do
3     case{1, 1, 1, 1, 1, 1, 1}  $\hat{f}_{i+1/2} = \hat{f}_{1,i+1/2}$ 
4     case{0, 1, 1, 1, 1, 1, 1}  $\hat{f}_{i+1/2} = \hat{f}_{2,i+1/2}$ 
5     case{1, 1, 1, 1, 1, 1, 0}  $\hat{f}_{i+1/2} = \hat{f}_{3,i+1/2}$ 
6     case else                call Algorithm 2.
7   endsw
8 end

```

Algorithm 3: The ninth-order scheme.

and ninth-order WENO schemes show lower dispersion. Moreover, the present schemes all show similar dispersion, probably because of using the same smoothness measurement. It is worth noting that the present schemes show somehow erratic spectral properties, especially in Fig. 2(b). This is because in the present schemes the stencil-selection procedure cannot switch between different candidate reconstructions smoothly. This behaviour can also be found in the result of the fifth-order ENO scheme, as shown in Ref. [21]. In Ref. [9], the novel TENO schemes having a stencil-selection procedure also show ADR results, in which the dispersion and dissipation do not change smoothly in high and intermediate wave-number regions. This issue has not yet been specifically addressed, to the authors' knowledge. However, as the excessive numerical dissipation in the nonlinear shock-capturing schemes usually damp the high-frequency waves, the minor irregular variation shown in Fig. 2(a) or Fig. 2(b) shouldn't be a critical issue.

In order to show the effect of changing the parameter C_T , Fig.3 is given, in which the ninth-order schemes are examined, to give an idea. Obviously, reducing C_T relaxes the criterion determining oscillatory stencils, and thus the

Figure 2: Approximate dispersion relation: $C_T = 10^{-2}$.

discrepancy between the underlying linear scheme and the present ninth-order scheme is also reduced. It should be noted that while C_T is sufficiently small, the dissipation could be even smaller than the ninth-order linear scheme, since centered stencils, e.g. $\hat{f}_{2,i+1/2}$, could be selected by the algorithms in the previous section. **Therefore, the parameter C_T can be adaptively tuned for achieving better performance [9], but this potential improvement is not discussed in this work for simplicity.**

Figure 3: Approximate dispersion relation: changing C_T .

Therefore, in general, we may conclude that the present schemes have competitive spectral performance compared with classical high-order WENO schemes.

4.2. shock-capturing error

The previous subsection provides the results showing the performance of resolving smooth waves. Here, the shock-capturing error analysis method [21] is implemented to examine the performance of capturing discontinuous solutions. In this scalar model problem, sinusoidal disturbances linearly propagate from the left to the right, and in the middle of the scalar field there is an abrupt change of the speed of sound, causing a fixed discontinuity. The present schemes and WENO schemes are investigated by solving this problem.

Firstly, the results of physical space are shown in Fig. 4. It can be clearly found that the fifth-order WENO scheme is dissipative and thus the post-shock smooth wave is smeared. The seventh-order WENO scheme is less dissipative. However, a significant overshoot can be found near the discontinuity. The present seventh-order scheme provides less dissipative result in this case and also has a smaller overshoot. Especially, the fifth- and seventh-order WENO schemes produce the overshoots and still show more dissipative smooth waves downstream. Moreover, the ninth-order WENO scheme shows more significant overshoot compared with the seventh-order WENO scheme, and the amplitude of the captured smooth wave in the post-shock region is even larger than the theoretical accurate solution. Therefore, it is difficult to **evaluate** the low-dissipation property of the ninth-order WENO scheme.

Then disturbances of different wave-number are introduced in this scalar model problem, to show the shock-capturing error in wave-number space. The results are shown in Fig. 5. Fig. 5(a) shows the amplitude error behind the discontinuity. It can be found that the fifth-order WENO scheme shows the smallest overshoot ($\epsilon_A > 0$), and then becomes dissipative ($\epsilon_A < 0$) for intermediate and high wave-number waves. The three present schemes show similar results, and they all provide smaller amplitude error compared with the seventh- and ninth-order WENO schemes. Especially, the ninth-order WENO scheme shows a very significant amplitude overshoot, which supports the result in Fig. 4(c). Furthermore, the phase error and total error are respectively shown in Fig. 5(b) and Fig. 5(c). The present schemes are less accurate in this case compared with the classical fifth-order WENO scheme, but significant advantages can be found compared with the higher-order WENO schemes, further supporting the results in physical space.

5. Canonical numerical tests

In the previous section, the present schemes are compared with the classical WENO schemes and the underlying upwind linear schemes, without considering the order of accuracy or complex phenomena. In this section, several canonical numerical cases involving the scalar advection equation and the Euler equations are solved, to show more details of the present schemes.

5.1. One-dimensional Gaussian pulse advection

The one-dimensional Gaussian pulse advection problem with a smooth initial field is used to assess the order of accuracy of the proposed schemes. This linear advection equation reads

$$\frac{\partial u}{\partial t} + \frac{\partial u}{\partial x} = 0, \quad x \in [0, 1]. \quad (16)$$

(a) 5th-order schemes

(b) 7th-order schemes

(c) 9th-order schemes

Figure 4: Shock-capturing error: physical space.

(a)

(b)

(c)

Figure 5: Shock-capturing error: spectral space.

Periodic boundary condition is applied in both side of the one-dimensional field, and the initial condition is

$$u(x, 0) = e^{-300(x-x_c)^2}, \quad x_c = 0.5. \quad (17)$$

Temporal integration is performed up to $t = 1$, corresponding to one period of the single wave propagation in time. Uniformly-spaced grids are progressively refined by a factor of two from the coarsest grid of $N = 41$ points. The numerical simulations are conducted using sufficiently small time steps such that temporal converged results are achieved, and only the spatial accuracy is investigated.

As shown in Fig. 6, the present schemes fully recover the accuracy of the underlying linear schemes. On the other hand, although the WENO schemes also show high-order of accuracy, they fail to recover the linear schemes in this case. Therefore, although only the simple five-point smoothness measurement is used, high-order of accuracy is still achieved by using the present method.

Figure 6: Numerical error of one-dimensional Gaussian pulse advection simulations.

It is worth noting that the present schemes are able to recover the underlying linear schemes because the smoothness measurement is effective in this case. However, as shown in the ADR analysis, the present schemes are not able to recover the linear schemes for high-frequency waves. Moreover, in order to improve the performance at smooth critical points, the smoothness measurement needs to be improved [8, 6, 7], and further investigation is to be provided for the present method.

5.2. Shock-density wave interaction

The shock-density wave interaction problem [34] is characterized by a right moving Mach 3 shock interacting with a sine wave in the density field. The multi-scale wave structure evolves after the shock wave interacts with the smooth density wave, and thus both the shock-capturing capability and wave-resolution performance can be evaluated. Regarding this gas dynamic problem, the Euler equations are solved as the governing equations, and these well known formulas are not specified here for simplicity.

The problem is initialized by

$$(\rho, u, p) = \begin{cases} (3.857, 2.629, 10.333), & x \in [0, 1], \\ (1 + 0.2\sin(5x), 0, 1), & x \in (1, 10]. \end{cases} \quad (18)$$

This case is run on a grid of $N = 161$ points which are uniformly distributed and the final time is $t = 1.8$. Specifically, the temporal solutions use 180 fixed time steps, i.e. $\Delta t = 0.01$. **Numerical solution of the fifth-order WENO-JS scheme** on a grid of $N = 2001$ is used as the reference solution. It should be noted that here we use a coarse mesh to examine the numerical schemes.

Numerical results of the fifth-, seventh- and ninth-order schemes are shown in Figs. 7, 8 and 9, respectively. It can be found the present fifth- and seventh-order schemes show significant better resolution compared with the corresponding WENO schemes. The present ninth-order scheme only shows minor improvement compared with the ninth-order WENO scheme. It is probably because only a sparse mesh is used, the advantage of high-order accuracy cannot be fully revealed in this case.

Figure 7: Density distribution of shock-density wave interaction problem: 5th-order schemes.

5.3. Interacting blast waves

The two-blast-wave interaction problem [35] is numerically simulated in this subsection. Because of the strong shock waves, this case is a challenging case for examining the robustness of shock-capturing schemes. Again, the Euler equations are solved as the governing equations, and the initial condition of this case is

$$(\rho, u, p) = \begin{cases} (1, 0, 1000), & x \in [0, 0.1], \\ (1, 0, 0.01), & x \in (0.1, 0.9], \\ (1, 0, 100), & x \in (0.9, 1]. \end{cases} \quad (19)$$

(a)

(b)

Figure 8: Density distribution of shock-density wave interaction problem: 7th-order schemes.

(a)

(b)

Figure 9: Density distribution of shock-density wave interaction problem: 9th-order schemes.

Reflective boundary condition is imposed at the boundary grid points.

This case is run on a grid of $N = 401$ points which are uniformly distributed and the final time is $t = 0.038$. Specifically, the temporal solutions use 1900 fixed time steps. Numerical solution of the fifth-order WENO-JS scheme on a grid of $N = 4001$ is used as the reference solution. Here, the seventh- and ninth-order WENO schemes couldn't complete the simulations due to the strong shock-waves. Therefore, the results of the present seventh- and ninth-order schemes are shown in Fig. 10, and thus the robustness of the present method are proved. Both the fifth-order WENO-JS scheme and the present fifth-order scheme are able to robustly capture the interacting shock waves in this case, but the results are similar and thus omitted.

Figure 10: Interacting blast waves problem simulated using the present 7th- and 9th-order schemes.

5.4. 2D Riemann problem: configuration 3

In this subsection, the 2D Riemann problem (configuration 3) in Ref. [36] is simulated to show the multi-dimensional performance of the present schemes. The initial conditions of configuration 3 are given by

$$(\rho, u, v, p) = \begin{cases} (1.5, 0, 0, 1.5) & x \in [0, 0.5] \text{ and } y \in [0, 0.5], \\ (0.5323, 1.206, 0, 0.3) & x \in [-0.5, 0) \text{ and } y \in [0, 0.5], \\ (0.138, 1.206, 1.206, 0.029) & x \in [-0.5, 0) \text{ and } y \in [-0.5, 0), \\ (0.5323, 0, 1.206, 0.3) & x \in [0, 0.5] \text{ and } y \in [-0.5, 0), \end{cases} \quad (20)$$

and extrapolate condition is given in all the boundaries. The grid has 801×801 points, and the results of the fifth-, seventh- and ninth-order schemes at $t = 0.3$ are given in Figs. 11, 12 and 13 respectively. Specifically, the temporal solutions use 1000 fixed time steps, i.e. $\Delta t = 0.0003$.

In general, the present schemes always show more vortices along the contact lines. It should be noted that the numerically-produced turbulence does not necessarily represent physics. Shi et al. [22] suggested that during mesh

Table 2: The overall running time (s) of the solver solving the configuration 3 of 2D Riemann problems.

	5th-order	7th-order	9th-order
WENO	5961.4	8119.5	11069.1
Present	6526.0	7100.8	8239.4

refinement slip lines usually are non-physically developing and depending on numerical schemes being used. However, more numerical vortices indicate a lower magnitude of numerical viscosities, which are necessary to guarantee that the physical viscosity in Navier-Stokes flow simulations is not overwhelmed by the numerical dissipation.

Figure 11: Configuration 3 of 2D Riemann problems: 5th-order schemes. Thirty equally spaced contour lines are drawn from $\rho = 0.2$ to $\rho = 1.7$.

Moreover, the overall running time of the solver is given in Table 2. The flow simulation results indicate that while increasing the order of accuracy, the computational effort of the present schemes increases less significantly compared with classical WENO schemes, because only the five-point smoothness measurement is applied. Especially, the present computing time includes the calculations of characteristic field and the temporal solution, etc., and the reason that increases the computing time of the present seventh- and ninth-order schemes is that these higher-order schemes need to calculate the characteristic variables at more grid points. Therefore, in the present method, using the relatively simpler smoothness measurement for higher-order schemes is indeed improving the computational efficiency.

It shall also be noted that, the symmetricity of the flow field is broken by the present schemes, especially the seventh- and ninth-order schemes. This phenomenon was also found in simulations using high-order WENO schemes [22]. Fleischmann et al. [37] have investigated this issue, and suggested that the symmetry-breaking actually relates to vanishing numerical viscosity and is driven by algorithmic floating-point effects which cannot be hidden by the numerical viscosity. They have thus proposed a procedure to solve this issue, by numerical and algorithmic formulations which respect floating-point arithmetic. However, this issue is not further discussed to avoid introducing more factors in the present comparison.

(a) WENO7

(b) present-7

Figure 12: Configuration 3 of 2D Riemann problems: 7th-order schemes. Thirty equally spaced contour lines are drawn from $\rho = 0.2$ to $\rho = 1.7$.

(a) WENO9

(b) present-9

Figure 13: Configuration 3 of 2D Riemann problems: 9th-order schemes. Thirty equally spaced contour lines are drawn from $\rho = 0.2$ to $\rho = 1.7$.

5.5. 2D Riemann problem: configuration 6

In this subsection, the 2D Riemann problem (configuration 6) in Ref. [36] is simulated. The initial conditions for the configuration 6 are given by

$$(\rho, u, v, p) = \begin{cases} (1, 0.75, -0.5, 1) & x \in [0, 0.5] \text{ and } y \in [0, 0.5], \\ (2, 0.75, 0.5, 1) & x \in [-0.5, 0] \text{ and } y \in [0, 0.5], \\ (1, -0.75, 0.5, 1) & x \in [-0.5, 0] \text{ and } y \in [-0.5, 0], \\ (3, -0.75, -0.5, 1) & x \in [0, 0.5] \text{ and } y \in [-0.5, 0]. \end{cases} \quad (21)$$

Here, the boundary condition and the spatial and temporal discretizations are also the same as those of the previous case.

The numerical results of the fifth-, seventh- and ninth-order schemes are shown in Figs. 14, 15 and 16, respectively. Again, the present schemes capture more vortices along the slip lines, compared with the WENO schemes. **Moreover, the computational cost of this case is similar to that of the previous case**, and thus the computing time is not shown for simplicity.

Figure 14: Configuration 6 of 2D Riemann problems: 5th-order schemes. Thirty equally spaced contour lines are drawn from $\rho = 0.1$ to $\rho = 4.0$.

However, it is worth noting again that using this (or the previous) inviscid flow problem for numerically examining the numerical resolution of high-order schemes might be arguable, because the vortices generated in this case are purely numerical. However, this is in fact the reason of using this numerical case, as the magnitude of numerical viscosity can be compared by examining the numerically generated vortices. For instance, Shi et al. [22] provided a numerical study to estimate the numerical viscosity of WENO schemes, using two inviscid numerical cases. In this work, the small structures captured by the present schemes clearly relate to the reduced numerical viscosity.

(a) WENO7

(b) present-7

Figure 15: Configuration 6 of 2D Riemann problems: 7th-order schemes. Thirty equally spaced contour lines are drawn from $\rho = 0.1$ to $\rho = 4.0$.

(a) WENO9

(b) present-9

Figure 16: Configuration 6 of 2D Riemann problems: 9th-order schemes. Thirty equally spaced contour lines are drawn from $\rho = 0.1$ to $\rho = 4.0$.

6. Conclusion

In order to achieve more flexible and efficient high-order spatial reconstructions, a new framework which detects discontinuities in a unified manner is designed. In this framework, the smoothness measurement of the five-point WENO scheme is used for shock-detection in the whole computation domain. Especially, the shock-detection procedure is done before the spatial reconstruction, without regarding the order of the spatial reconstruction schemes. The smoothness measurement defined on the typical five-point full stencil is proved to be efficient and reliable.

The essential advantage of the present method is that: since the locations of all the discontinuities are known before the spatial reconstruction, basically arbitrary high-order reconstruction can be applied, as long as the known smooth region is large enough. Therefore, complicated smoothness indicators such as those of the higher-order WENO schemes are not required, reducing the computational effort of using a higher-order scheme (higher than fifth-order).

In this work, up to ninth-order schemes are designed, and their performance is examined by using the state-of-the-art analyzing methods, including the ADR **analysis** and the novel shock-capturing error metric, and also various canonical test cases. In particular, the present seventh- and ninth-order schemes are more efficient than the classical WENO schemes. For example, the overall CPU time required by the solver with using the present ninth-order scheme is 74.4% of the CPU time required for using the ninth-order WENO scheme. It should be noted that the computational cost includes all the cost of spatial reconstruction, flux-splitting and time integration, etc. Within the present framework, higher than ninth-order schemes are also expectable and to be investigated.

Acknowledgments

This work was partially supported by the Open fund from State Key Laboratory of Aerodynamics (Grant No. SKLA20180302).

References

- [1] A. Harten, B. Engquist, S. Osher, S. R. Chakravarthy, Uniformly high order accurate essentially non-oscillatory schemes, III, *Journal of Computational Physics* 71 (2) (1987) 231–303. doi:10.1016/0021-9991(87)90031-3.
- [2] X. D. Liu, S. Osher, T. Chan, Weighted essentially non-oscillatory schemes, *Journal of Computational Physics* 115 (1) (1994) 200–212. doi:10.1006/jcph.1994.1187.
- [3] G.-S. Jiang, C.-W. Shu, Efficient implementation of weighted ENO schemes, *Journal of Computational Physics* 126 (1) (1996) 202–228. doi:10.1006/jcph.1996.0130.
- [4] D. Drikakis, M. Hahn, A. Mosedale, B. Thornber, Large eddy simulation using high-resolution and high-order methods, *Philosophical Transactions Royal Society A* 367 (1899). doi:10.1098/rsta.2009.0065.
- [5] K. Ritos, I. W. Kokkinakis, D. Drikakis, Performance of high-order implicit large eddy simulations, *Computers & Fluids* 173 (2018) 307–312. doi:10.1016/j.compfluid.2018.01.030.

- [6] R. Borges, M. Carmona, B. Costa, W. S. Don, An improved weighted essentially non-oscillatory scheme for hyperbolic conservation laws, *Journal of Computational Physics* 227 (6) (2008) 3191–3211. doi:10.1016/j.jcp.2007.11.038.
- [7] W.-S. Don, R. Borges, Accuracy of the weighted essentially non-oscillatory conservative finite difference schemes, *Journal of Computational Physics* 250 (2013) 347 – 372. doi:10.1016/j.jcp.2013.05.018.
- [8] A. K. Henrick, T. D. Aslam, J. M. Powers, Mapped weighted essentially non-oscillatory schemes: Achieving optimal order near critical points, *Journal of Computational Physics* 207 (2) (2005) 542–567. doi:10.1016/j.jcp.2005.01.023.
- [9] L. Fu, X. Y. Hu, N. A. Adams, A new class of adaptive high-order targeted ENO schemes for hyperbolic conservation laws, *Journal of Computational Physics* 374 (2018) 724–751. doi:10.1016/j.jcp.2018.07.043.
- [10] H. Dong, L. Fu, F. Zhang, Y. Liu, J. Liu, Detonation simulations with a fifth-order TENO scheme, *Communications in Computational Physics* 25 (2019) 1357–1393. doi:10.4208/cicp.0A-2018-0008.
- [11] S. Pirozzoli, Conservative hybrid compact-weno schemes for shock-turbulence interaction, *Journal of Computational Physics* 178 (1) (2002) 81–117. doi:10.1006/jcph.2002.7021.
- [12] X. Y. Hu, B. Wang, N. A. Adams, An efficient low-dissipation hybrid weighted essentially non-oscillatory scheme, *Journal of Computational Physics* 301 (2015) 415424. doi:10.1016/j.jcp.2015.08.043.
- [13] G.-Y. Zhao, M.-B. Sun, S. Pirozzoli, On shock sensors for hybrid compact/WENO schemes, *Computers & Fluids* 199 (2020) 104439. doi:10.1016/j.compfluid.2020.104439.
- [14] G.-Y. Zhao, M.-B. Sun, Y. Mei, L. Li, H.-B. Wang, G.-X. Li, Y. Liu, Y.-C. Sun, C.-H. Liang, An efficient adaptive central-upwind WENO-CU6 numerical scheme with a new sensor, *Journal of Scientific Computing* 81 (2019) 649670. doi:10.1007/s10915-019-01035-9.
- [15] D. S. Balsara, C.-W. Shu, Monotonicity preserving weighted essentially non-oscillatory schemes with increasingly high order of accuracy, *Journal of Computational Physics* 160 (2) (2000) 405 – 452. doi:10.1006/jcph.2000.6443.
- [16] G. Gerolymos, D. Sénéchal, I. Vallet, Very-high-order WENO schemes, *Journal of Computational Physics* 228 (23) (2009) 8481 – 8524. doi:10.1016/j.jcp.2009.07.039.
- [17] X. Deng, H. Zhang, Developing high-order weighted compact nonlinear schemes, *Journal of Computational Physics* 165 (1) (2000) 22 – 44. doi:10.1006/jcph.2000.6594.
- [18] H. Zhang, F. Zhang, C. Xu, Towards optimal high-order compact schemes for simulating compressible flows, *Applied Mathematics and Computation* 355 (2019) 221–237. doi:10.1016/j.amc.2019.03.001.

- [19] Z. Tian, G. Wang, F. Zhang, H. Zhang, A third-order compact nonlinear scheme for compressible flow simulations, *International Journal for Numerical Methods in Fluids* 92 (10) (2020) 1352–1367. doi:10.1002/flid.4831.
- [20] A. Suresh, H. Huynh, Accurate monotonicity-preserving schemes with rungekutta time stepping, *Journal of Computational Physics* 136 (1) (1997) 83 – 99. doi:10.1006/jcph.1997.5745.
- [21] G. Zhao, M. Sun, A. Memmolo, S. Pirozzoli, A general framework for the evaluation of shock-capturing schemes, *Journal of Computational Physics* 376 (2019) 924–936. doi:10.1016/j.jcp.2018.10.013.
- [22] J. Shi, Y.-T. Zhang, C.-W. Shu, Resolution of high order weno schemes for complicated flow structures, *Journal of Computational Physics* 186 (2) (2003) 690 – 696. doi:10.1016/S0021-9991(03)00094-9.
- [23] D. Sun, F. Qu, C. Yan, An efficient adaptive high-order scheme based on the WENO process, *Computers & Fluids* 140 (2016) 81 – 96. doi:10.1016/j.compfluid.2016.09.011.
- [24] J. Peng, C. Zhai, G. Ni, H. Yong, Y. Shen, An adaptive characteristic-wise reconstruction weno-z scheme for gas dynamic euler equations, *Computers & Fluids* 179 (2019) 34 – 51. doi:10.1016/j.compfluid.2018.08.008.
- [25] D. Sun, F. Qu, J. Bai, C. Yan, An effective low dissipation method for compressible flows, *Aerospace Science and Technology* 100 (2020) 105757. doi:10.1016/j.ast.2020.105757.
- [26] F. Zhang, J. Liu, H. Zhang, C. Xu, An extending strategy based on teno framework for hyperbolic conservation laws, arXiv:1808.00037v4 [physics.comp-ph] (2018).
- [27] H. Zhang, F. Zhang, J. Liu, J. McDonough, C. Xu, A simple extended compact nonlinear scheme with adaptive dissipation control, *Communications in Nonlinear Science and Numerical Simulation* 84 (2020) 105191. doi:10.1016/j.cnsns.2020.105191.
- [28] S. Gottlieb, C. Shu, E. Tadmor, Strong stability-preserving high-order time discretization methods, *SIAM Review* 43 (1) (2001) 89–112. doi:10.1137/S003614450036757X.
- [29] Z. Sun, S. Inaba, F. Xiao, Boundary variation diminishing (bvd) reconstruction: A new approach to improve godunov schemes, *Journal of Computational Physics* 322 (2016) 309 – 325. doi:10.1016/j.jcp.2016.06.051.
- [30] X. Deng, Y. Shimizu, F. Xiao, A fifth-order shock capturing scheme with two-stage boundary variation diminishing algorithm, *Journal of Computational Physics* 386 (2019) 323–349. doi:10.1016/j.jcp.2019.02.024.
- [31] X. Deng, Y. Shimizu, B. Xie, F. Xiao, Constructing higher order discontinuity-capturing schemes with upwind-biased interpolations and boundary variation diminishing algorithm, *Computers & Fluids* 200 (2020) 104433. doi:10.1016/j.compfluid.2020.104433.
- [32] M. Castro, B. Costa, W. S. Don, High order weighted essentially non-oscillatory weno-z schemes for hyperbolic conservation laws, *Journal of Computational Physics* 230 (5) (2011) 1766–1792. doi:10.1016/j.jcp.2010.11.028.

- [33] S. Pirozzoli, On the spectral properties of shock-capturing schemes, *Journal of Computational Physics* 219 (2) (2006) 489 – 497. doi:10.1016/j.jcp.2006.07.009.
- [34] C.-W. Shu, S. Osher, Efficient implementation of essentially non-oscillatory shock-capturing schemes,ii, *Journal of Computational Physics* 83 (1) (1989) 32–78. doi:10.1016/0021-9991(89)90222-2.
- [35] P. Woodward, P. Colella, The numerical simulation of two-dimensional fluid flow with strong shocks, *Journal of Computational Physics* 54 (1) (1984) 115–173. doi:10.1016/0021-9991(84)90142-6.
- [36] P. Lax, X. Liu, Solution of two-dimensional riemann problems of gas dynamics by positive schemes, *SIAM Journal on Scientific Computing* 19 (2) (1998) 319–340. doi:10.1137/S1064827595291819.
- [37] N. Fleischmann, S. Adami, N. A. Adams, Numerical symmetry-preserving techniques for low-dissipation shock-capturing schemes, *Computers & Fluids* 189 (2019) 94 – 107. doi:10.1016/j.compfluid.2019.04.004.